


DVR-605

SERVICE MANUAL

(DVT-605)

This manual is available for U.S.A. and Canada markets.



In compliance with Federal Regulations, following are reproduction of labels on, or inside the product relating to laser product safety.

Caution : No connection of ground line if disassemble the unit. Please connect the ground line on rear panel, PCBs, Chassis and some others.

KENWOOD Corp. certifies this equipment conforms to DHHS Regulations No.21 CFR 1040. 10, Chapter 1, subchapter J.

DANGER : Laser radiation when open and interlock defeated. AVOID DIRECT EXPOSURE TO BEAM.









DVR-605

CONTENTS / ACCESSORIES / CAUTIONS

Contents

CONTENTS / ACCESSORIES / CAUTIONS	2	PC BOARD	14
DISASSEMBLY FOR REPAIR	3	SCHEMATIC DIAGRAM	22
BLOCK DIAGRAM	3	EXPLODED VIEW	35
CIRCUIT DESCRIPTION	4	PARTS LIST	36
ADJUSTMENT	13	SPECIFICATIONS	Back cover
INTERCONNECTION DIAGRAM	13		

Accessories

<p>FM indoor antenna (1) (T90-0882-08)</p> 	<p>Loop antenna (1) (T90-0896-08)</p> 	<p>Video cord (1) (E30-1427-05)</p> 	<p>Speaker cords (6) (E30-7265-08): RED (E30-7283-08): GREEN (E30-7284-08): BLUE (E30-7285-08): VIOLET (E30-7269-08): GREY (E30-7286-08): WHITE</p> 
<p>Remote control unit (1) (A70-1607-08)</p> 	<p>Batteries (R6/AA) (2)</p> 		

Cautions

Caution on condensation

Condensation (of dew) may occur inside the unit when there is a great difference in temperature between this unit and the outside.

This unit may not function properly if condensation occurs. In this case, leave the unit for a few hours, and restart the operation after the condensation has dried up.

Be specially cautious against condensation in a following circumstances:

When this unit is carried from one place to another across a large difference in temperature, when the humidity in the room where this unit is installed increases, etc.

Memory backup function

Stored contents which are cleared in at least a week after power plug is unplugged from power outlet.

Amplifier section

Last input selection
Volume control value
Surround setting
ACTIVE EQ

Tuner section

Receiving band
Frequency
Preset stations
Tuning mode setting

DVD section


Menu setup

Power status

Note related to transportation and movement
Before transporting or moving this unit, carry out the following operations.

❶ Remove the disc from the unit.

❷ Press the ►/II key.



❸ Wait a few seconds and turn the unit OFF.

WARNING NOTICE:

IN MOST CASES IT IS AN INFRINGEMENT OF COPYRIGHT TO MAKE COPIES OF TAPES OR DISCS WITHOUT THE PERMISSION OF THE COPYRIGHT OWNERS. ANYONE WISHING TO COPY COMMERCIALY AVAILABLE TAPES OR DISC SHOULD CONTACT THE MECHANICAL COPYRIGHT PROTECTION SOCIETY LIMITED OR THE PERFORMING RIGHTS SOCIETY LIMITED.

Operation to reset

The microcomputer may fall into malfunction (impossibility to operate, erroneous display, etc.) when the power cord is unplugged while power is ON or due to an external factor. In this case, execute the following procedure to reset the microcomputer and return it to normal condition.

Set the POWER switch to ON (set to Standby mode). Then press the ►► key, ◀◀ key and STOP key in this order.

- Please note that resetting the microcomputer clears the contents stored in and returns to condition when it left the factory.

The marking of products using lasers (Except for some areas)

**CLASS 1
LASER PRODUCT**


The marking this product has been classified as Class 1. It means that there is no danger of hazardous radiation outside the product.
Location: Back panel

DISASSEMBLY FOR REPAIR / BLOCK DIAGRAM


DISASSEMBLY FOR REPAIR

How to open the tray if it does not come out.

1. Insert a flat driver in the drawing through the hole on the loading chassis bottom and pull the lever down.
2. Pull out the tray frontward by hand when it comes just out.



BLOCK DIAGRAM



CIRCUIT DESCRIPTION

1. Pin Description of MPEG Processor IC (DVD Part IC61)

Pin No.	Pin Name	I/O	Pin Description
PIOs and communication			
1	PIO2(5) RGB SEL(BLANK)	I/O	RGB sel (blank). unused
2	PIO2(6) VIDEO MUTE	I/O	Video mute control.
3	PIO2(7) 16: 9 INDICATOR	I/O	16 : 9 indicator (unused).
6	PIO3(0) SCART H (TV/AUX)	I/O	Unused.
7	PIO3(1)	I/O	Unused.
8	PIO3(2)	O	CSB
* 9	PIO3(3)	O	SDIN
10	PIO3(4) IR REMOCON	I/O	Unused.
* 11	PIO3(5)	O	SCLK
12	PIO3(6)	I/O	Unused.
13	PIO3(7) DVD RESET	I/O	Power- on reset of front-end module.
Front-end			
16	B DATA	I	I2S Data
17	B BCLK	I	I2S Bit clock
18	B FLAG	I	I2S Error flag
19	B SYNC	I/O	I2S Sector / ABS time
Reserved			
20	B WCLK	I/O	Unused.
21	B V4	I/O	Unused.
22	NRSS OUT	I/O	Unused.
23	VDD RGB	-	Supply voltage for RGB (+3.3VA).
24	VSS RGB	-	GND
Video DAC			
25,26,27	B/G/R (OUT)	O	B/G/R signal outputs.
28	V REF RG	I	Reference voltage input for DAC RGB.
29	I REF RG	I	Reference current input for DAC RGB.
30	VDD YCC	-	Supply voltage for YCC (+3.3VA).
31	VSS YCC	-	GND
32~34	Y/C/CV (OUT)	O	Y/C/CV signal outputs.
35	V REF YCC	I	Reference voltage input for DAC YCC.
36	I REF YCC	I	Reference current input for DAC YCC.
PIOs and communication			
39	PIO4(0)HP MUTE	-	Unused.
40	PIO4(1)	-	Unused.
41	PIO4(2)	O	DAC system clock output.
42	PIO4(3) DAC RESET	O	DAC reset output.
43	PIO4(4) PLL CS	O	DAC mute control.
44	PIO4(5) DAC CLOCK	O	DAC clock output
45	PIO4(6) DAC DATA	O	DAC data output.
46	PIO4(7) DAC CS	O	DAC chip select.
Audio DAC			
48	VDD PCM	-	Supply voltage for PCM (+3V3).
49	VSS PCM	-	Ground for PCM.
51	DAC SCLK (BCK)	O	DAC over sampling clock.
52	DAC PCMOUT0 (DATA)	O	DAC PCM data out 0.
53	DAC PCMOUT1	O	DAC PCM out 1 (unused).
54	DAC PCMOUT2	O	DAC PCM out 2 (unused).
55	DAC PCMCLK	O	DAC PCM clock.
56	DAC LRCLK	O	DAC PCM Left/Right clock.
57	SPDIF OUT	O	Audio digital data output.
Shared memory interface			
58~63	SMI ADR(4~9)	O	SDRAM address bus.
66~69	SMI ADR(3~0)	O	SDRAM address bus.

CIRCUIT DESCRIPTION

Pin No.	Pin Name	I/O	Pin Description
70~73	SMI ADR(10~13)	O	SDRAM address bus.
74	SMI CS(0)	O	Chip select bank 0.
75	SMI CS(1)	-	Unused.
76	SMI RAS	O	SDRAM RAS
77	SMI CAS	O	SDRAM CAS
78	SMI WE	O	SDRAM write enable.
79	SMI DQML	O	DQ MASK enable low.
80	SMI DQMU	O	DQ MASK enable up.
82	SMI CLKIN	I	SDRAM clock input.
84~93	SMI DATA(0~9)	I/O	SDRAM data bus.
95	SMI CLKOUT	O	SDRAM clock out.
97~102	SMI DATA(10~15)	I/O	SDRAM data bus.
Reserved			
* 103	ADC SCLK	I/O	ADC digital audio port clock.
* 104	ADC LRCLK	I/O	ADC sample rate clock.
* 105	ADC DATA	I	ADC digital audio data input.
* 106	ADC PCMCLK	O	Crystal input or master clock input.
JTAG			
109	TRST	I	Test reset from emulator module.
110	TMS	I	Test mode select.
111	TDO	O	Test data out to emulator module.
112	TDI	I	Test data input from emulator module.
113	TCK	I	Test clock input from emulator module.
Timers			
114	PWM2	I/O	Unused.
115	PWM1	I/O	ROM boot option port (voltage low = emulator booting).
116	PWM0	I/O	Unused.
EMI Interface			
117	CPU OE	I/O	Flash ROM output enable
118	CPU PRO CLK	O	SDRAM clock (unused).
Clock & Reset			
120	PIX CLK	I	27MHz main clock input.
122	VDD PLL	-	Supply voltage for PLL (+3V3).
123	VSS PLL	-	Ground for PLL.
124	RESET	I	Chip reset input.
Interrupt			
125	IRQ(2)	I	Interrupt request 2 from front-end module.
126	IRQ(1)	I	Unused.
127	IRQ(0)	I	Unused.
EMI Interface			
128	CPU BE(0)	O	BYTE 0 Enable
129	CPU BE(1)	O	BYTE 1 Enable
130	CPU RW	O	Unused.
131	CPU WAIT	I	Wait state (connected to ground).
132	CPU CE(3)	O	Flash ROM chip select.
133	CPU CE(2)	O	Flash ROM down-load JIG module select.
134	CPU CE(1)	O	Unused
135	CPU CE(0)	O	Unused.
138	CPU RAS1	I/O	Unused.
139	CPU CAS0	O	Unused.
140	CPU CAS1	O	Unused.
141~148	CPU DATA(0~7)	I/O	Flash ROM data input/output (0~7).
151~158	CPU DATA(8~15)	I/O	Flash ROM data input/output (8~15).
161~170	CPU ADR(1~10)	O	Flash ROM address (1~10).
173~183	CPU ADR(11~21)	O	Flash ROM address (11~21).

CIRCUIT DESCRIPTION

Pin No.	Pin Name	I/O	Pin Description
PIOs and communication			
186	PIO0(0) T STROBE	I/O	UART0 data
187	PIO0(1) MOD SW	I/O	ATAPI RD
188	PIO0(2)	O	Unused.
189	PIO0(3)	O	Unused.
190	PIO0(4)	O	Unused.
191	PIO0(5)	I	Unused.
192	PIO0(6) SLIDER SENSOR OPEN/CLOSE (DRAWER POSITION)	I/O	Detection port of slider sensor for DVD mechanism.
193	PIO0(7) SLIDER IN (DRAWER CCW/CTRL)	I/O	Control port of slider (IN) for DVD mechanism.
194	PIO1(0) SDA	I/O	SSC0 data (MSTR out / MRST in)
195	PIO1(1) SCL	I/O	SSC0 clock
196	PIO1(2) SLIDER OUT (DRAWER CW CTRL)	I/O	Control port of slider (OUT) for DVD mechanism.
197	PIO1(3) TXD(JIG)	I/O	UART2 TXD
200	PIO1(4) RXD(JIG)	I/O	UART2 RXD
201	PIO1(5) FRONT TXDI	I/O	UART1 TXD
202	TRIGGER IN	I/O	Trigger input from JIG.
203	TRIGGER OUT	I/O	Trigger output from JIG.
204	PIO2(0) H/P	-	Unused.
205	PIO2(1) FRONT RXD	I/O	UART1 RXD
206	PIO2(2)	I	Unused.
207	PIO2(3)	-	Unused.
208	PIO2(4) AUDIO MUTE	O	Audio mute control.
Power supply			
4,47,81,107 136,159,184	VDD3 3	-	3.3V Power supply.
14,37,64,94 119,149,171 198	VDD2 5	-	2.5V Power supply.
5,15,38,50,65 83,96,108,121 137,150,160 172,185,199	VSS	-	GND

* M Type only

2. Pin Description of System Microcomputer : CXP82860(Microprocessor IC51)

Pin No.	Pin Name	I/O	Description
1	GRID2	O	FIP Grid output.
2	GRID1	O	FIP Grid output.
3	NC	-	Connected to VDD.
4	POWER DOWN	I	Power down check.
5	RDS CLK	I	RDS clock input.
6	DVD RX	I	DVD UART interface (RX).
7	RDS OPTION	-	Unused.
8	RMC	I	Remote controller signal input.
9	RDS DATA	I	RDS data input.
10	SM7346 CLK	O	Volume IC (IC11) clock output.
11	SM7346 DATA	O	Volume IC (IC11) data output.
12	ENCODER UP	I	Encoder (1) signal input.
13	ENCODER DW	I	Encoder (2) signal input.
14	DVD TX	O	DVD UARTinterface (TX).
15	DVD RST	O	DVD reset signal output.

CIRCUIT DESCRIPTION

Pin No.	Pin Name	I/O	Description
16	DSP A. BOOST	O	DSP auto boot.
17	H/P CHK	I	Detection pin of headphones jack.
18	CS8415A-CE	O	DIR IC (IC39) chip enable.
19	EMPHASIS	O	CS4228 DAC IC emphasis ON/OFF
20	TUNED	I	Tuned signal input for tuner.
21	DSP INTREQ	O	DSP INT request.
22	4094CE	O	4049 (IC81)chip enable.
23	CS49326 CE	O	CS49326 DSP IC (IC33) chip enable.
24	CS4228 CE	O	CS4228 DAC IC (IC31) chip enable.
25	DSP CLK	O	CS49326 DSP IC (IC33) clock output.
26	CS49326 DATA IN	I	CS49326 DSP IC (IC33) data input.
27	DSP DA OUT	O	CS49326 DSP IC (IC33) data output.
28	VREF	I	A/D reference voltage input.
29	PROTECT	I	AMP protection input.
30	KEY IN	I	A/D key input.
31	EEPROM DATA	I/O	EEPROM (IC52) data output.
32	KEY2 IN	I	A/D key input.
33	8415 DA IN	I	CS8415 DIR IC (IC39) data input.
34	DVD OPTION	I	Setting pin for the destination.
35	PLL DATA IN	I	PLL data input.
36	STEP OPTION	I	Setting pin for tuner destination.
37	VSS(G)	I	Analog ground.
38	RST	I	Reset signal input.
39	EXTAL	I	Crystal resonator (10MHz) connection.
40	XTAL	O	Crystal resonator (10MHz) connection.
41	GND	-	Digital ground.
42	NC	O	Unused.
43	GND	-	GND
44	VDD	I	Digital ground.
45	VFDP	I	Power supply for VFDP.
46	STANDBY	O	Control pin for power relay on/off.
47	SPK RELAY	O	Control pin for speaker relay on/off.
48	SUB ON/OFF	O	Gain control for sub woofer.
49	CS8415 RST	O	CS8415 (IC39) reset signal output.
50	PLL CE	O	PLL chip enable.
51	PLL CLK	O	PLL clock output.
52	PLL D OUT	O	PLL data output.
53	A CLK	O	Common clock (LC7821,BU4094) output.
54	A DATA	O	Common data (LC7821,BU4094) output.
55	EEPROM CLK	O	EEPROM (IC52) clock output.
56~59	VIDEO (SW1~SW4)	O	Control pin for video.
60	4228 RST	O	CS4228 (IC31) reset signal output.
61	LC7821 CE	O	LC7821(tuner pack) chip enable.
62	SM7346 CE	O	Volume IC (Main IC11) chip enable.
63	T MUTE	O	Tuner mute control.
64	S MUTE	O	Mute control pin for surround signal
65	C MUTE	O	Mute control pin for center signal.
66	F MUTE	O	Mute control pin for front signal.
67	W MUTE	O	Mute control pin for sub woofer signal.
68	CS49326 RST	O	CS49326 DSP IC (IC5) reset signal output.
69~71	DSP (A15~A17)	O	DSP ROM address (SEL 1~3).
72~88	SEG (1~17)	O	FIP segment output.
89	VDD	-	Digital power supply.
90,91	SEG18,19	O	FIP segment output.
92-100	GRID (11~3)	O	FIP Grid output.

CIRCUIT DESCRIPTION

3. Pin Description of IC's

3-1 64 Bit SDRAM : HY57V641620HGT (DVD Part IC63)

Pin No.	Pin Name	I/O	Description
38	CLK	I	The system clock input. all other inputs are registered to the SDRAM on the rising edge of CLK.
37	CKE	-	Controls internal clock signal and when deactivated, the SDRAM will be one of the states among power down, suspend or self refresh.
19	CS	-	Enables or disables all inputs except CLK, CKE, and DQM.
20,21	BA0,BA1	-	Selects bank to be activated during RAS activity. Selects bank to be read/written during CAS activity.
22~26 29~35	A0~A11	-	Row address : RA0~RA11, Column address : CA0~CA7 Auto-precharge flag : A10
16,17,18	WE,CAS,RAS	-	WE, CAS and RAS define the operation.
15,39	LDQM,UDQM	I/O	Controls output buffers in read mode and masks input data in write mode.
2,4,5,7,8,10 11,13,42,44 45,47,48,50 51,53	DQ0~DQ15	I/O	Multiplexed data input/output pin.
1,3,9,14,27 43,49	VCC/VCC Q	-	Power supply for internal circuits and input buffers.
6,12,28,41, 46,52,54	VSS/VSS Q	-	Ground terminal.
36,40	NC	-	Unused.

3-2 24-bit, 192kHz Stereo DAC : WM8728 (DVD Part IC64)

Pin No.	Pin Name	I/O	Description
1	LRCIN	I	DAC sample rate clock input : PCM input mode Right channel DSD bitstream input : DSD input mode
2	DIN	I	Serial audio data input : PCM input mode Left channel DSD bitstream input : DSD input mode
3	BCKIN	I	Audio data bit clock input.
4	MCLK	I	Master clock input.
5	ZERO	O	Infinite zero detect flag.
6	DGND	-	Digital ground supply.
7	DVDD	-	Digital positive supply.
8	VOUTr	O	Right channel DAC output.
9	AGND	-	Analog ground supply.
10	AVDD	-	Analog positive supply.
11	VOUtl	O	Left channel DAC output.
12	VMID	O	Mid rail decoupling point.
13	VREFN	-	DAC negative reference.
14	VREFP	-	DAC positive reference.
15	CSBIWL	I	Software mode : 3-wire serial control chip select Hardware mode : Input word length
16	MODE	I	Control mode selection.
17	MUTEB	-	Mute control. "L" = Mute on, "H" = Mute off
18	SDIDEM	-	Software mode : 3 or 2-wire serial control data input Hardware mode : De-Emphasis select
19	SCKDSD	I	Software mode : 3 or 2-wire serial control clock input Hardware mode : DSD bitstream operation select
20	LAT12S	I	Software mode : 3-wire serial control load input Hardware mode : Input data format selection

DVR-605

CIRCUIT DESCRIPTION

3-3 Flash Memory : SST39VF800A904 (DVD Part IC66)

Pin No.	Pin Name	I/O	Description
1~8, 16~25,48	A0~A18	I	Address Inputs
29,31,33,35,38,40 42,44	DQ0~DQ7	I/O	Data Input/Outputs, Command Inputs
30,32,34,36,39,41,43	DQ8~DQ14	I/O	Data Input/Outputs
45	DQ15	I/O	Data Input/Outputs or Address input
26	CE	-	Chip Enable
28	QE	-	Output Enable
11	WE	-	Write Enable
12	RP	-	Reset/Block Temporary Unprotect
15	RY/BY	O	Ready/Busy/Output(Unused)
47	BYTE	-	Byte/Word Organization
37	VCC	-	Supply Voltage
27,46	VSS	-	Ground

3-4 HEX Inverter (Single Stage) : M74HCU04 (DVD Part IC67)

Pin No.	Pin Name	I/O	Pin Description
1,3,5,9, 11,13	A0 to A5	I	Data Inputs
2,4,6,8, 10,12	Q0 to Q5	O	Data Outputs
7	GND	-	Ground
14	VCC	-	Positive Supply Voltage

Truth Table

A	Q
L	H
H	L


3-5 Video Driver : MM1540AF (DVD Part IC68)

Pin No.	Pin Name	I/O	Description
1,28	VCC1,2	-	VCC
2	VIN	I	Unused
3	YC MIX	-	YC MIX select (GND)
4	CIN	I	Croma input
5	CLP	-	Clamp select (Connected to VCC)
6,9	YIN (1,2)	I	Video input (Composite or Y)
7	MUTE 1	O	Mute select (GND)
8	MUTE 2	O	Mute select
10	GND	-	GND
11,13	CbIN, CrIN	I	Component input
12	Dual/Single	-	Power select (+5V)
14,15,19, 21,22,24	VEE1, VEE2	-	VEE (-5V)
16,18,20, 23,25,27	CrOUT, CbOUT, YOUT2,YOUT1, COUT,VOUT	O	Video output
17,26	PS2,PS1	-	Power save (Connected to GND)

3-6 DC Motor Driver : FAN8082(DVD Part IC69)

Pin No.	Pin Name	I/O	Pin Description
1	GND	-	Ground
2	VO1	O	Output 1
3	VCTL	I	Motor speed control
4	VIN1	I	Input 1
5	VIN2	I	Input 2
6	SVCC	-	Supply voltage (Signal)
7	PVCC	-	Supply voltage (Power)
8	VO2	O	Output 2

Internal Block Diagram



CIRCUIT DESCRIPTION

3-7 Stereo Audio ADC : VM8739 (DVD Part IC70) M Type only

Pin No.	Pin Name	I/O	Pin Description
1	SDIN	I	3-wire MPU data input/2-wire MPU data input.
2	SCLK	I	3-wire MPU clock input/2-wire MPU clock input.
3	XTI/MCLK	I	Crystal input or master clock input (MCLK).
4	XTO	O	Crystal output.
5	DCVDD	-	Digital core VDD.
6	DGND	-	Digital GND.
7	DBVDD	-	Digital buffers VDD.
8	BCLK	I/O	Digital audio port clock.
9,10	DNC	-	Unused.
11	ADCDAT	O	ADC digital audio data output.
12	ADCLRC	I/O	ADC sample rate clock.
13	NC	-	Unused.
14	AVDD	-	Analog VDD.
15	AGND	-	Analog GND.
16	VMID	O	Mid-rail reference decoupling point.
17	R IN	I	Right channel line input (AC coupled).
18	L IN	I	Left channel line input (AC coupled).
19	MODE	I	Control interface selection, pull up (on power up only).
20	CSB	I	3-wire MPU chip select/2-wire MPU interface address selection.

3-8 Volume Control IC: M62446AFP (Main B' D IC11)

Pin No.	Pin Name	I/O	Pin Description
1~4	OUT(4~1)	O	Unused.
5	AVDD	-	Power supply (+7.0V) for analog.
6	SWin	I	Volume input for SW channel.
7,10,12,14	GND(S,C,R,L)	-	Analog ground.
8	SRin	I	Volume input for SR channel.
9	SLin	I	Volume input for SL channel.
11	Cin	I	Volume input for center channel.
13	Rin	I	Tone input for FR channel.
15	Lin	I	Tone input for FL channel.
16,17	BYPASS(R,L)	I	Input pin of the volume input selector when bypass.
18,25	LTRE/RTRE	-	Frequency characteristic setting pin in the tone control (Treble).
19,24,20, 23,21,22	LBASS3/RBASS3 LBASS2/RBASS2 LBASS1/RBASS1	-	Frequency characteristic setting pin in the tone control (Bass).
26,28	CR2/CL2	O	Tone output.
27,29	CR1/CL1	I	Input pin of the main volume.
30	AVSS	-	Power supply (-7.0V) for analog.
31	L OUT	O	Output pin of the main volume.
32	R OUT	O	Output pin of the main volume.
33~36	C/SL/SR/SW(OUT)	O	Output pin of the main volume.
37	AGND	-	Analog ground.
38	DGND	-	Digital ground.
39	LATCH	I	Latch input.
40	DATA	I	Input pin of the serial data.
41	CLK	I	Clock input.
42	DVDD	-	Power supply (+5.0V) for digital.

CIRCUIT DESCRIPTION

3-9 Power Amplifier : LM4766 (Main B' D IC18)

Pin No.	Pin Name	Pin Description
1	FLCH A	Audio FL channel output.
2	FRCH VCC	Power supply (+B) for FR channel.
3	FRCH OUT	Audio FR channel output.
4	VEE	Power supply (-B)
5	FRCH GND	FRch GND
6	FRCH MUTE	Mute control pin of FR channel.
7	FRCH NF	Feed back of FR channel.
8	FRCH IN	Audio FR channel input.
9	NC	Unused.
10	FLCH GND	FLch GND
11	FLCH MUTE	Mute control pin of FL channel.
12	FLCH NF	Feed back of FL channel.
13	FLCH IN	Audio FL channel input.
14	NC	Unused.
15	FLCH VCC	Power supply (+B) for FL channel.

3-10 ADC & DAC : CS4228 (DSP B' D IC31)


Pin No.	Pin Name	I/O	Pin Description
1~3	SDIN(3~1)	I	Serial data (3~1) input.
4	SDOUT	O	Serial data output.
5	SCLK	I/O	Audio output bit clock.
6	LRCLK	I/O	Audio output sample rate clock.
7	DGND	-	Digital ground.
8,9	VD,VL	-	+3.3V digital power supplies.
10	MCLK	I/O	Audio master clock.
11	SCL/CCLK	I	Serial control interface clock.
12	SDA/CDIN	I	Serial control data input.
13	AD0/CS	I	Address bit / Control port chip select
14	RST	I	Master reset input.
15	MUTEC	-	Unused.
16	AINR+	I	Analog signal input (+) connection for the right channel.
17	AINR-	I	Analog signal input (-) connection for the right channel.
18	FILT	-	PLL loop filter pin.
19	AINL-	I	Analog signal input (-) connection for the left channel.
20	AINL+	I	Analog signal input (+) connection for the left channel.
21	VA	-	+5.0V analog power supply.
22	AGND	-	Analog ground for clock generator PLL.
23~28	AOUT(1~6)	O	The analog outputs from the D/A converters.

CIRCUIT DESCRIPTION

3-11 Digital Audio Decoder : CS493263 (DSP B' D IC33)

Pin No.	Pin Name	I/O	Pin Description
1,12,23	VDD(1~3)	-	Digital positive supplies.
2,13,24	VSS(1~3)	-	Digital ground.
3	XMT958	0	SPDIF transmitter output (unused).
4	WR,DS	I/O	Host Write Strobe, Host Data Strobe, External Memory Write Enable or General Purpose Input
5	RD,RW	I/O	Host Parallel Output Enable, Host parallel R/W, External Memory Output Enable, General Purpose Input
6	A1, SCDIN	1	Host address bit one or SPI serial control data input.
7	A0, SCCLK	I	Host parallel address bit zero or serial control pin clock.
8~11 14~17	DATA(7~0)	I/O	Data bus (7~0).
18	CS	I	Chip select input.
19	SCDI0,SCDOUT	I/O	Serial control data input and output.
20	INTREQ ABOUT	I/O	Control pin interrupt request, automatic boot enable.
21	EXTMEM	I/O	External memory chip select input/output.
22	SDATAN	I	PCM audio data input.
25	SCLKN	I/O	PCM audio input bit clock.
26	SLRCLKN	I/O	PCM audio input sample rate clock.
27	CMPDAT	I	PCM audio data input.
28	CMPCLK	I/O	PCM audio input bit clock.
29	CMPREQ	I/O	PCM audio input sample rate clock.
30	CLKIN	I	Master clock input.
31	CLKSEL	I	DSP clock select.
32	FLT2	-	Phase locked loop filter.
33	FLT1	-	Phase locked loop filter.
34	VDDA	-	Analog positive power supply for clock generator.
35	VSSA	-	Analog ground for clock generator PLL.
36	RESET	I	Master reset input.
37	DD	I/O	This pin should be pulled up with an external 4.7k Ω resistor.
38	DC	I	This pin should be pulled up with an external 4.7k Ω resistor.
39	AUDAT2	O	Digital audio output 2.
40	AUDAT1	O	Digital audio output 1.
41	AUDAT0	O	Digital audio output 0.
42	LRCLK	I/O	Audio output sample rate clock.
43	SCLK	I/O	Audio output bit clock.
44	MCLK	I/O	Audio master clock.

4. Block Diagram of Shift Register : BU4094 (Front IC81)



ADJUSTMENT / INTERCONNECTION DIAGRAM

No.	ITEM	INPUT SETTING	OUTPUT SETTING	ALIGNMENT POINT	ALIGNMENT FOR	FIG.
1	<i>Progressive Y LEVEL</i>	100% COLOR BAR DISC	Connect the oscilloscope to Y output(NJ13) with 75-ohms resistor. ※ Output Mode: Progressive	VR11	Y-signal= 1000mV±100mV	FIG.1










The diagram illustrates the internal architecture of the DVD-R605 system, organized into several functional blocks:

- u-COM B'D**: The central control unit, featuring a microprocessor (N501) and various control logic components (N502, N503, N504, N505, N506, N507, N508, N509, N510, N511, N512, N513, N514, N515, N516, N517, N518, N519, N520, N521, N522, N523, N524, N525, N526, N527, N528, N529, N530, N531, N532, N533, N534, N535, N536, N537, N538, N539, N540, N541, N542, N543, N544, N545, N546, N547, N548, N549, N550, N551, N552, N553, N554, N555, N556, N557, N558, N559, N560, N561, N562, N563, N564, N565, N566, N567, N568, N569, N570, N571, N572, N573, N574, N575, N576, N577, N578, N579, N580, N581, N582, N583, N584, N585, N586, N587, N588, N589, N590, N591, N592, N593, N594, N595, N596, N597, N598, N599, N600, N601, N602, N603, N604, N605, N606, N607, N608, N609, N610, N611, N612, N613, N614, N615, N616, N617, N618, N619, N620, N621, N622, N623, N624, N625, N626, N627, N628, N629, N630, N631, N632, N633, N634, N635, N636, N637, N638, N639, N640, N641, N642, N643, N644, N645, N646, N647, N648, N649, N650, N651, N652, N653, N654, N655, N656, N657, N658, N659, N660, N661, N662, N663, N664, N665, N666, N667, N668, N669, N670, N671, N672, N673, N674, N675, N676, N677, N678, N679, N680, N681, N682, N683, N684, N685, N686, N687, N688, N689, N690, N691, N692, N693, N694, N695, N696, N697, N698, N699, N700, N701, N702, N703, N704, N705, N706, N707, N708, N709, N710, N711, N712, N713, N714, N715, N716, N717, N718, N719, N720, N721, N722, N723, N724, N725, N726, N727, N728, N729, N730, N731, N732, N733, N734, N735, N736, N737, N738, N739, N740, N741, N742, N743, N744, N745, N746, N747, N748, N749, N750, N751, N752, N753, N754, N755, N756, N757, N758, N759, N760, N761, N762, N763, N764, N765, N766, N767, N768, N769, N770, N771, N772, N773, N774, N775, N776, N777, N778, N779, N780, N781, N782, N783, N784, N785, N786, N787, N788, N789, N790, N791, N792, N793, N794, N795, N796, N797, N798, N799, N800, N801, N802, N803, N804, N805, N806, N807, N808, N809, N810, N811, N812, N813, N814, N815, N816, N817, N818, N819, N820, N821, N822, N823, N824, N825, N826, N827, N828, N829, N830, N831, N832, N833, N834, N835, N836, N837, N838, N839, N840, N841, N842, N843, N844, N845, N846, N847, N848, N849, N850, N851, N852, N853, N854, N855, N856, N857, N858, N859, N860, N861, N862, N863, N864, N865, N866, N867, N868, N869, N870, N871, N872, N873, N874, N875, N876, N877, N878, N879, N880, N881, N882, N883, N884, N885, N886, N887, N888, N889, N890, N891, N892, N893, N894, N895, N896, N897, N898, N899, N900, N901, N902, N903, N904, N905, N906, N907, N908, N909, N910, N911, N912, N913, N914, N915, N916, N917, N918, N919, N920, N921, N922, N923, N924, N925, N926, N927, N928, N929, N930, N931, N932, N933, N934, N935, N936, N937, N938, N939, N940, N941, N942, N943, N944, N945, N946, N947, N948, N949, N950, N951, N952, N953, N954, N955, N956, N957, N958, N959, N960, N961, N962, N963, N964, N965, N966, N967, N968, N969, N970, N971, N972, N973, N974, N975, N976, N977, N978, N979, N980, N981, N982, N983, N984, N985, N986, N987, N988, N989, N990, N991, N992, N993, N994, N995, N996, N997, N998, N999, N1000).
- STANDBY LED B'D**: Controls the standby LED (P802).
- SWITCH B'D**: Controls the system switch (P801).
- FRONT VIDEO INPUT B'D**: Receives video signals from the front panel (P803, P812, P813).
- FRONT B'D**: Front panel interface (N809, N810, N811, N812, N813, N814, N815, N816, N817, N818, N819, N820, N821, N822, N823, N824, N825, N826, N827, N828, N829, N830, N831, N832, N833, N834, N835, N836, N837, N838, N839, N840, N841, N842, N843, N844, N845, N846, N847, N848, N849, N850, N851, N852, N853, N854, N855, N856, N857, N858, N859, N860, N861, N862, N863, N864, N865, N866, N867, N868, N869, N870, N871, N872, N873, N874, N875, N876, N877, N878, N879, N880, N881, N882, N883, N884, N885, N886, N887, N888, N889, N890, N891, N892, N893, N894, N895, N896, N897, N898, N899, N900, N901, N902, N903, N904, N905, N906, N907, N908, N909, N910, N911, N912, N913, N914, N915, N916, N917, N918, N919, N920, N921, N922, N923, N924, N925, N926, N927, N928, N929, N930, N931, N932, N933, N934, N935, N936, N937, N938, N939, N940, N941, N942, N943, N944, N945, N946, N947, N948, N949, N950, N951, N952, N953, N954, N955, N956, N957, N958, N959, N960, N961, N962, N963, N964, N965, N966, N967, N968, N969, N970, N971, N972, N973, N974, N975, N976, N977, N978, N979, N980, N981, N982, N983, N984, N985, N986, N987, N988, N989, N990, N991, N992, N993, N994, N995, N996, N997, N998, N999, N1000).
- DSP B'D**: Digital Signal Processor (N301, N302, N303, N304, N305, N306, N307, N308, N309, N310, N311, N312, N313, N314, N315, N316, N317, N318, N319, N320, N321, N322, N323, N324, N325, N326, N327, N328, N329, N330, N331, N332, N333, N334, N335, N336, N337, N338, N339, N340, N341, N342, N343, N344, N345, N346, N347, N348, N349, N350, N351, N352, N353, N354, N355, N356, N357, N358, N359, N360, N361, N362, N363, N364, N365, N366, N367, N368, N369, N370, N371, N372, N373, N374, N375, N376, N377, N378, N379, N380, N381, N382, N383, N384, N385, N386


1
2
3
4
5
6
7


DIGITAL IN COAXIAL


K	L	M	N	O	P	Q	R	S	T
---	---	---	---	---	---	---	---	---	---




PC BOARD(Component side view)







The DC voltage is an actual reading measured with a high impedance type voltmeter with no signal input. The measurement value may vary depending on the measuring instruments used or on the product.




CAUTION: For continued safety, replace safety critical components only with manufacturer's recommended parts (refer to parts list). Δ indicates safety critical components. For continued protection against risk of fire, replace only with same type and rating fuse(s). To reduce the risk of electric shock, leakage-current or resistance measurements shall be carried out (exposed parts are acceptably insulated from the supply circuit) before the appliance is returned to the customer.


The DC voltage is an actual reading measured with a high impedance type voltmeter with no signal input. The measurement value may vary depending on the measuring instruments used or on the product.

DVR-605
KENWOOD

Y39-4480-10








DVR-6100		J501	R525	R531	R541	R542
DESTINATION	COUNTRY	ABB.				
JAPAN	J	NO	YES	NO	NO	1.2K
PK	Y	YES				4.7K
AUSTRALIA	X					1.2K
U.K.	T					
EUROPE	E					

DVR-6100K		J501	R525,531,541,542	R542
DESTINATION	COUNTRY	ABB.		
KOREA	H		NO	3.9K
GENERAL MARKET	M	YES		
GENERAL MARKET	M2			1.2K

DVR-605		J501	R525,531,541,542	R542
DESTINATION	COUNTRY	ABB.		
U.S.A.	K	NO	NO	
CANADA	P			




IC51 : CXP82860-366Q
IC52 : M24C02WMN6
IC53 : NJM2296

Q501 : KTC3875Y

D501,507 : 1N4148
D502-506,551,552 : 1SS355



POWER B'D- P505

AS-7




FRONT B'D

	6G	5G	4G	3G	2G	1G
P1	1a	1a	1a	1a	1a	1a
P2	1b	1b	1b	1b	1b	1b
P3	SEQ.	1c	1c	1c	1c	1c
P4	1	1d	1d	1d	1d	1d
P5	2	1e	1e	1e	1e	1e
P6	—	1f	1f	1f	1f	1f
P7	DVD	1g	1g	1g	1g	1g
P8	VCD	—	1h	HOUR	MIN	SEC
P9	CD	TITLE	1n	1n	REPEAT	1n
P10	MP3	—	CHAP	col	col	—
P11	2a	2a	2a	2a	—	—
P12	PCB	2b	2b	2b	2b	—
P13	—	2c	2c	2c	2c	—
P14	—	2d	2d	2d	2d	—
P15	—	2e	2e	2e	2e	—
P16	—	2f	2f	2f	2f	—
P17	—	2g	2g	2g	2g	A
P18	—	INTRO	TRACK	2j	2j	B
P19	—	Dp	Dp	RANDOM	1	DISC
P20	(1)	(3)	(5)	PROG.	ALL	S
P21	—	(2)	(4)	—	—	—
P22	1	3	5	—	—	—
P23	—	2	4	—	—	—



DVR-605 (4/4)



CAUTION: For continued safety, replace safety critical components only with manufacturer's recommended parts (refer to parts list). Δ indicates safety critical components. For continued protection against risk of fire, replace only with same type and rating fuse(s). To reduce the risk of electric shock, leakage-current or resistance measurements shall be carried out (exposed parts are acceptably insulated from the supply circuit) before the appliance is returned to the customer.


The DC voltage is an actual reading measured with a high impedance type voltmeter with no signal input. The measurement value may vary depending on the measuring instruments used or on the product.

DVR-605

KENWOOD

Y39-4480-10

EXPLODED VIEW (UNIT)



* New Parts

Parts without **Parts No.** are not supplied.

Les articles non mentionnés dans le **Parts No.** ne sont pas fournis.

Teile ohne **Parts No.** werden nicht geliefert.

①

Ref. No	Add-ress	New Parts	Parts No.	Description	Desti-nation	Re-marks
DVR-605						
601	2A	*	B07-2651-08	DEC CABINET	55316850#1	
602	2A	*	B10-3897-08	MLD INDICATO	55316820#22	
603	2A	*	K29-8248-08	DEC BUTTON I	55316850#10	
604	2A	*	B10-3898-08	MLD INDICATO	55316830#26	
606	2A	*	K29-8249-08	DEC KNOB MAI	55316740#5	
607	2B	*	K29-8250-08	DEC BUTTON P	55316690#25	
608	2B		D21-2932-08	PLASTIC MLD	55220710#49	
611	2A	*	K29-8251-08	DEC BUTTON O	55316670#24	
612	2A	*	K29-8252-08	DEC BUTTON C	55316640#21	
613	2A	*	K29-8253-08	DEC BUTTON O	55316660#20	
614	2A	*	K29-8254-08	DEC BUTTON P	55316680#13	
615	2A	*	B07-2655-08	DEC RING/BUT	55316810#12	
616	2A	*	K29-8255-08	DEC BUTTON S	55316700#11	
617	2A	*	B07-2656-08	DEC DOOR FUN	55316720#8	
618	2A	*	K29-8256-08	DEC BUTTON S	55316710#14	
620	2B,1C	*	E35-3452-08	FFC-300M/M 19X	21178300	
621	1B	*	B07-2657-08	DEC DOOR TRA	55316730#2	
622	2A	*	B10-3899-08	DEC CRYSTAL	55316770#7	
623	2A	*	B10-3900-08	DEC CRYSTAL	55316760#4	
624	2A	*	B07-2658-08	CPL DOOR PLA	55316800#9	
625	2B	*	E35-3453-08	FFC-80M/M 19X	55181200	
626	2A	*	G11-2914-08	RAW SHIELD R	55189590#6	
636	1B		A01-3863-08	PUN COVER TO	55220680#56	
638	1C		J42-0350-08	MLD CLAMP AC	55125180#48	
639	1C		E30-2991-08	WIRE-MCRDM	55099250#47	
641	1B		D40-1787-08	OK TVM 502 T	10718640#55	
644	2C	*	L07-3234-08	TF-LAM POWER	55328180	
645	1C	*	W02-2964-08	EPR TUNER MO	5516112A	
649	1B		W02-2929-08	MSA ASY SMPS	55161420	
651	2A,2C		J02-1544-08	FOOT CUSHION	55220690#3	
654	2B,2C		J19-6169-08	MLD BRACKET	55164980#54	
655	2A,1C		E35-3273-08	FFC-JUMPER 33X	55164010	
656	1C		E35-3271-08	FFC-JUMPER 13X	55328220	
659	2A,1C		E35-3272-08	FFC-JUMPER 11X	55163980	
660	1C		E35-3271-08	FFC-JUMPER 13X	55163940	
661	1A		T90-0882-08	ANTENNA WIRE	55127470	
662	1A		T90-0896-08	ANTENNA LOOP	55208620	
663	1A		E30-7265-08	WIRE-SP 4M,RD	55236710	
664	1A	*	E30-7283-08	WIRE-SP 4M,GN	55236730	
665	1A	*	E30-7284-08	WIRE-SP 8M,BU	55380840	
666	1A	*	E30-7285-08	WIRE-SP 4.5M,VT	55380850	
667	1A	*	E30-7269-08	WIRE-SP 8M,GY	55192270	
668	1A	*	E30-7286-08	WIRE-SP 4M,WH	55380860	
669	1A	*	A70-1607-08	EPR RCT REMOC	55393340	
670	2B		L92-0560-08	FCORE FERRIT	55177290	
672	1A		E30-1427-05	WIRE-CABSP AUDI	55192120	
-		*	B60-5262-08	BOOK INSTR(EN)	55349890	
△ F251			F50-0073-05	FUSULSLWBL 2.5	20828870	
-			H10-7818-08	MAT-PKG CUSHI	5520874A	
-			H10-7883-08	POLYSTYRENE FOAMED FIXTURE L		
-			H10-7884-08	POLYSTYRENE FOAMED FIXTURE R		
-			H21-1514-08	SHEET EPE RT	55135940	
-			H25-1712-08	CPL BAG RCA	55170650	

L : Scandinavia

K : USA

P : Canada

R : Mexico

C : China

I : Malaysia

Y : PX(Far East,Hawaii)

T : England

E : Europe

G : Germany

V : China(Shanghai)

Y : AAFES(Europe)

X : Australia

Q : Russia

H : Korea

M : Other Areas

△ indicates safety critical components .

* New Parts

Parts without **Parts No.** are not supplied.

Les articles non mentionnés dans le **Parts No.** ne sont pas fournis.

Teile ohne **Parts No.** werden nicht geliefert.

②

Ref. No	Add-ress	New Parts	Parts No.	Description	Desti-nation	Re-marks
-			H25-1715-08	CPL BAG PE C	20715540	
-			H25-1731-08	CPL BAG POLY	55237020	
-			H25-1732-08	CPL BAG PE 4	55030950	
-		*	H50-4588-08	CARTON DVR60	55333230	
E			N09-5269-08	SCREW-ST 3MM	55127290	
△ IC18,9			LM4766T	IC(AUDIO POWER	AMPLIFIER)	
IC20-2			TDA7294	IC-POWAMP	TDA7294	
POWER SUPPLY						
△ C251,2			C91-1645-08	CERAMIC	0.0047UF	250VAC
△ R251			R92-1844-05	CARBON	3.3M	J 1/2W
△ SK21			S76-0137-08	RELAYPWR 5.0V	55183470	
△ S251			S90-0149-08	SWIPUSH POWER	55141570	
D251			1N4148	D-SLP	1N4148	
Q251			DTC114YSA	TR-SLPLF	DTC114YSA	
MAIN PCB						
C 1			CC73GCH1H220J	CHIP C	22PF	J
C 2-6			CC73GCH1H330J	CHIP C	33PF	J
C 7			CK73GB1H102K	CHIP C	1000PF	K
C 8			CK73GB1H331J	CHIP C	330PF	J
C 9,10			CK73GB1H102K	CHIP C	1000PF	K
C 11-25			CC73GCH1H101J	CHIP C	100PF	J
C 26-8			CC73GCH1H471J	CHIP C	470PF	J
C 29			CK73GB1C104K	CHIP C	0.10UF	K
C 30-5			CK73GB1H102K	CHIP C	1000PF	K
C 36-9			CC73GCH1H470J	CHIP C	47PF	J
C 40-3			CE04LW1H4R7M	ELECTRO	4.7UF	50WV
C 44			CC73GCH1H220J	CHIP C	22PF	J
C 45			CK73GB1H331J	CHIP C	330PF	J
C 50,1			CC73GCH1H101J	CHIP C	100PF	J
C 52			CC73GCH1H220J	CHIP C	22PF	J
C 53,4			CK73GB1C104K	CHIP C	0.10UF	K
C 55			CC73GCH1H220J	CHIP C	22PF	J
C 56			CC73GCH1H471J	CHIP C	470PF	J
C 57-60			CC73GCH1H470J	CHIP C	47PF	J
C 63,4			CC73GCH1H101J	CHIP C	100PF	J
C 65			CK73GB1H331J	CHIP C	330PF	J
C 66-9			CC73GCH1H101J	CHIP C	100PF	J
C 71,2			CK73GB1H102K	CHIP C	1000PF	K
C 73-8			CK73GB1H103K	CHIP C	0.010UF	K
C 79-81			CC73GCH1H101J	CHIP C	100PF	J
C 82			CE04LW1H220M	ELECTRO	22UF	50WV
C 83			CE04LW1H010M	ELECTRO	1.0UF	50WV
C 84			CQ92M1H153K	MYLAR	0.015UF	K
C 85,6			CE04LW1HR33M	ELECTRO	0.33UF	50WV
C 87			CQ92M1H153K	MYLAR	0.015UF	K
C 88,9			CE04LW1H220M	ELECTRO	22UF	50WV
C 90			CQ92M1H822K	MYLAR	8200PF	K
C 91,2			CE04LW1H3R3M	ELECTRO	3.3UF	50WV
C 94,5			CE04LW2A010M	ELECTRO	1.0UF	100WV
C 96			CE04LW1H2R2M	ELECTRO	2.2UF	50WV
C 97,8			CE04LW2A010M	ELECTRO	1.0UF	100WV

L : Scandinavia

K : USA

P : Canada

R : Mexico

C : China

I : Malaysia

Y : PX(Far East,Hawaii)

T : England

E : Europe

G : Germany

V : China(Shanghai)

Y : AAFES(Europe)

X : Australia

Q : Russia

H : Korea

M : Other Areas

△ indicates safety critical components .

PARTS LIST

DVR-605

* New Parts
Parts without **Parts No.** are not supplied.
Les articles non mentionnés dans le **Parts No.** ne sont pas fournis.
Teile ohne **Parts No.** werden nicht geliefert.

3

Ref. No	Add-ress	New Parts	Parts No.	Description	Desti-nation	Re-marks
C 99-107 C109,10 C111-6 C117,8 C119			CE04LW1H100M CE04LW1C470M CE04LW1H4R7M CE04LW1H100M CE04LW1H220M	ELECTRO 10UF 50WV ELECTRO 47UF 16WV ELECTRO 4.7UF 50WV ELECTRO 10UF 50WV ELECTRO 22UF 50WV		
C120-4 C129 C130-4 C135,6 C137,8			CE04LW1C470M CE04LW1H100M CQ92FM1H104K CE04LW1H100M CQ92FM1H104K	ELECTRO 47UF 16WV ELECTRO 10UF 50WV MYLAR 0.10UF K ELECTRO 10UF 50WV MYLAR 0.10UF K		
C139,40 C141,2 C143 C144-9 C150			CE04LW1H100M CQ92FM1H104K CE04LW1H100M CQ92FM1H102K CE04LW1H100M	ELECTRO 10UF 50WV MYLAR 0.10UF K ELECTRO 10UF 50WV MYLAR 1000PF K ELECTRO 10UF 50WV		
C151 C152,3 C154 C155 C156			CQ92FM1H102K CQ92FM1H104K CE04LW1H100M CQ92FM1H104K CE04LW1C470M	MYLAR 1000PF K MYLAR 0.10UF K ELECTRO 10UF 50WV MYLAR 0.10UF K ELECTRO 47UF 16WV		
C157 C158 C159-62 C163 C164			CQ92FM1H104K - CE04LW1H4R7M CQ92M1H822K CQ92FM1H104K	MYLAR 0.10UF K BCL 0.5MM TIN ELECTRO 4.7UF 50WV MYLAR 8200PF K MYLAR 0.10UF K		
C165 C166,7 C168,9 C170-2 C173			CE04LW1H100M CQ92FM1H223K CE04KW1H472M CQ92FM1H223K CE04KW1E332M	ELECTRO 10UF 50WV MYLAR 0.022UF K ELECTRO 4700UF 50WV MYLAR 0.022UF K ELECTRO 3300UF 25WV		
C174,5 C176,7 C178 C179 C180			CE04KW1E102M CE04LW1H4R7M CE04LW1H100M CE04LW1H221M CE04LW1H470M	ELECTRO 1000UF 25WV ELECTRO 4.7UF 50WV ELECTRO 10UF 50WV ELECTRO 220UF 50WV ELECTRO 47UF 50WV		
C181 C182 C183 C184 C185-9			CE04LW1H100M CE04KW1C102M CE04LW1C470M CE04LW1C101M CE04LW1H4R7M	ELECTRO 10UF 50WV ELECTRO 1000UF 16WV ELECTRO 47UF 16WV ELECTRO 100UF 16WV ELECTRO 4.7UF 50WV		
C190 C191 C192 C193 C194			CE04LW1C470M CE04LW1H220M CE04LW1A221M CE04LW1H2R2M CE04LW1A471M	ELECTRO 47UF 16WV ELECTRO 22UF 50WV ELECTRO 220UF 10WV ELECTRO 2.2UF 50WV ELECTRO 470UF 10WV		
C195 C196,7 C198 C199 C207			CE04LW1C101M CE04LW1H4R7M CE04LW1H100M CE04LW1C470M CE04LW1C470M	ELECTRO 100UF 16WV ELECTRO 4.7UF 50WV ELECTRO 10UF 50WV ELECTRO 47UF 16WV ELECTRO 47UF 16WV		
C208-11			CK73GB1H331J	CHIP C 330PF J		
N107 NJ11 NJ12			E41-0824-08 E70-0165-08 E63-1270-08	CONN 1.25MM 13 55124790 CONN-SPE TERMI 55237010 CON PHONO SCKT 55203340		

L : Scandinavia K : USA P : Canada R : Mexico C : China I : Malaysia
Y : PX(Far East,Hawaii) T : England E : Europe G : Germany V : China(Shanghai)
Y : AAFES(Europe) X : Australia Q : Russia H : Korea M : Other Areas ⚠ indicates safety critical components .

* New Parts
Parts without **Parts No.** are not supplied.
Les articles non mentionnés dans le **Parts No.** ne sont pas fournis.
Teile ohne **Parts No.** werden nicht geliefert.

4

Ref. No	Add-ress	New Parts	Parts No.	Description	Desti-nation	Re-marks
NJ13			E63-1271-08	CON PHONO SCKT 55192000		
L 1-7			L39-1624-08	LFA 1MM 10MM 7 21070690		
J 1 J 5 J 13 J 15 J 17			RK73GB1J000J RK73GB1J000J RK73GB1J000J RK73GB1J000J RK73GB1J000J	CHIP R 0 J 1/16W CHIP R 0 J 1/16W CHIP R 0 J 1/16W CHIP R 0 J 1/16W CHIP R 0 J 1/16W		
J 19 J 20,1 J 23 J 26 R 1,2			RK73GB1J000J RK73GB1J000J RK73GB1J000J RK73GB1J000J RK73GB1J123J	CHIP R 0 J 1/16W CHIP R 0 J 1/16W CHIP R 0 J 1/16W CHIP R 0 J 1/16W CHIP R 12K J 1/16W		
R 3,4 R 5 R 6 R 8,9 R 10			RK73GB1J222J RK73GB1J751J RK73GB1J272J RK73GB1J472J RK73GB1J102J	CHIP R 2.2K J 1/16W CHIP R 750 J 1/16W CHIP R 2.7K J 1/16W CHIP R 4.7K J 1/16W CHIP R 1.0K J 1/16W		
R 11,2 R 13 R 14 R 15 R 16			RK73GB1J103J RK73GB1J223J RK73GB1J102J RK73GB1J222J RK73GB1J472J	CHIP R 10K J 1/16W CHIP R 22K J 1/16W CHIP R 1.0K J 1/16W CHIP R 2.2K J 1/16W CHIP R 4.7K J 1/16W		
R 17 R 19 R 20 R 28,9 R 30			RK73GB1J103J RK73GB1J123J RK73GB1J681J RK73GB1J471J RK73GB1J681J	CHIP R 10K J 1/16W CHIP R 12K J 1/16W CHIP R 680 J 1/16W CHIP R 470 J 1/16W CHIP R 680 J 1/16W		
R 31-6 R 37-42 R 43,4 R 45 R 46-51			RK73GB1J561J RK73GB1J104J RK73GB1J272J RK73GB1J122J RK73GB1J103J	CHIP R 560 J 1/16W CHIP R 100K J 1/16W CHIP R 2.7K J 1/16W CHIP R 1.2K J 1/16W CHIP R 10K J 1/16W		
R 52-7 R 58-60 R 61 R 62 R 63-8			RK73GB1J104J RK73GB1J102J RK73GB1J302J RK73GB1J102J RK73GB1J473J	CHIP R 100K J 1/16W CHIP R 1.0K J 1/16W CHIP R 3.0K J 1/16W CHIP R 1.0K J 1/16W CHIP R 47K J 1/16W		
R 69-74 R 75-8 R 79,80 R 81 R 82-5			RK73GB1J102J RK73GB1J153J RK73GB1J224J RK73GB1J103J RK73GB1J102J	CHIP R 1.0K J 1/16W CHIP R 15K J 1/16W CHIP R 220K J 1/16W CHIP R 10K J 1/16W CHIP R 1.0K J 1/16W		
R 86,7 R 89 R 90 R 91 R 92-4			RK73GB1J223J RK73GB1J103J RK73GB1J123J RK73GB1J681J RK73GB1J333J	CHIP R 22K J 1/16W CHIP R 10K J 1/16W CHIP R 12K J 1/16W CHIP R 680 J 1/16W CHIP R 33K J 1/16W		
R 95-9 R100,1 R102 R108-13 R114,5			RK73GB1J332J RK73GB1J132J RK73GB1J332J RK73GB1J223J RK73GB1J471J	CHIP R 3.3K J 1/16W CHIP R 1.3K J 1/16W CHIP R 3.3K J 1/16W CHIP R 22K J 1/16W CHIP R 470 J 1/16W		
R117,8			RK73GB1J102J	CHIP R 1.0K J 1/16W		

L : Scandinavia K : USA P : Canada R : Mexico C : China I : Malaysia
Y : PX(Far East,Hawaii) T : England E : Europe G : Germany V : China(Shanghai)
Y : AAFES(Europe) X : Australia Q : Russia H : Korea M : Other Areas ⚠ indicates safety critical components .

PARTS LIST

* New Parts

Parts without **Parts No.** are not supplied.

Les articles non mentionnés dans le **Parts No.** ne sont pas fournis.

Teile ohne **Parts No.** werden nicht geliefert.

5

Ref. No	Add-ress	New Parts	Parts No.	Description	Desti-nation	Re-marks
R119,20 R121,2 R123,4 R125,6 R127,8			RK73GB1J223J RK73GB1J682J RK73GB1J683J RK73GB1J121J RK73GB1J332J	CHIP R 22K J 1/16W CHIP R 6.8K J 1/16W CHIP R 68K J 1/16W CHIP R 120 J 1/16W CHIP R 3.3K J 1/16W		
R129,30 R133,4 R135-8 R139-42 R145,6			RK73GB1J224J RK73GB1J471J RK73GB1J104J RK73GB1J471J RK73GB1J751J	CHIP R 220K J 1/16W CHIP R 470 J 1/16W CHIP R 100K J 1/16W CHIP R 470 J 1/16W CHIP R 750 J 1/16W		
R147 R148 R149 R150 R151,2			RK73GB1J564J RK73GB1J332J RK73GB1J564J RK73GB1J223J RK73GB1J222J	CHIP R 560K J 1/16W CHIP R 3.3K J 1/16W CHIP R 560K J 1/16W CHIP R 22K J 1/16W CHIP R 2.2K J 1/16W		
R156 R157,8 R159,60 R161 R179,80			RK73GB1J222J RK73GB1J332J RK73GB1J102J RK73GB1J104J RK73GB1J224J	CHIP R 2.2K J 1/16W CHIP R 3.3K J 1/16W CHIP R 1.0K J 1/16W CHIP R 100K J 1/16W CHIP R 220K J 1/16W		
R181,2 R185-7 R189 R190 R191			RK73GB1J273J RS14GB3D391J RS14GB3A4R7J RS14GB3A271J RS14GB3A4R7J	CHIP R 27K J 1/16W FL-PROOF RS 390 J 2W FL-PROOF RS 4.7 J 1W FL-PROOF RS 270 J 1W FL-PROOF RS 4.7 J 1W		
△ R233,4 R235,6 R242 R243 R244			RS14GB3A1R0J RS14GB3A271J R92-4582-08 RS14GB3A220J	FL-PROOF RS 1 J 1W BCL 0.5MM TIN 20441260 FL-PROOF RS 270 J 1W METAL PLATE 0.1 J 5W FL-PROOF RS 22 J 1W		
R249,50 R252 R253 R254			RK73GB1J822J RK73GB1J473J RS14GB3A101J RK73GB1J473J	CHIP R 8.2K J 1/16W CHIP R 47K J 1/16W FL-PROOF RS 100 J 1W CHIP R 47K J 1/16W		
SK11-3			S76-0136-08	RELAYPWR 24.0V 55091520		
D 1,2 D 3 D 4,5 D 7-12 D 13			1N4148 1N5230B 1N4148 EK03 1N4148	D-SLP 1N4148 D-ZENER 1N5230B D-SLP 1N4148 D-SR SCHOTTKY EK03 D-SLP 1N4148		
D 14-9 D 20,1 D 22 △ D 23-31 D 32			EK03 1N4148 BU6-04F 1N4004 1SS355	D-SR SCHOTTKY EK03 D-SLP 1N4148 D-BRDLC BU6-04F D-SR 1N4004 D-SLP 1SS355		
D 33 D 34 D 35-8 D 39 D 40,1			BZX55B30 1N5236B 1N4148 BZX85C12 1N5235B	D-ZENER BZX55B30 D-ZENER 1N5236B D-SLP 1N4148 D-ZENER BZX85C12 D-ZENER 1N5235B		
D 42-4 D 45 IC 11 IC 12,3		*	1N4148 1SS355 M62446AFP NJM2068DD	D-SLP 1N4148 D-SLP 1SS355 IC-LOWFREQ M62446AFP IC-OPERAMP NJM2068DD		

L : Scandinavia K : USA P : Canada R : Mexico C : China I : Malaysia
Y : PX(Far East,Hawaii) T : England E : Europe G : Germany V : China(Shanghai)
Y : AAFES(Europe) X : Australia Q : Russia H : Korea M : Other Areas △ indicates safety critical components .

* New Parts

Parts without **Parts No.** are not supplied.

Les articles non mentionnés dans le **Parts No.** ne sont pas fournis.

Teile ohne **Parts No.** werden nicht geliefert.

6

Ref. No	Add-ress	New Parts	Parts No.	Description	Desti-nation	Re-marks
△ IC 14 △ IC 15-7 △ IC 23 △ IC 24 △ IC 25			LC78211 NJM2068DD KIA7815API KIA7915PI BA033T	IC-SWITCH LC78211 IC-OPERAMP NJM2068DD IC-REGPOSF XD KIA7815API IC-REGNEGF XD KIA7915PI IC(ANALOGUE IC) BA033T		
△ IC 26 Q 12 Q 13-8 Q 19,20 Q 21			KIA7805API KTA1266 KTD1302 KTA1266 KTC3200GR	IC(VOLTAGE REGULATOR) TR-SLPLF KTA1266 TR-SLPLF KTD1302 TR-SLPLF KTA1266 TR-SHPLF KTC3200BL		
△ Q 22 Q 23 Q 26 Q 27,28 Q 30,31			KTA1268 KTA1023 DTA114YSA KTD1302 KTD1302	TR-SLPLF KTA1268 GR TR-SLPLF 55211430 TR-SLPLF DTA114YSA TR-SLPLF KTD1302 TR-SLPLF KTD1302		
Q 33-35 Q 36-8 Q 41 Q 42			DTA114YSA DTC114YSA 2SC1740S 2SA933S	TR-SLPLF DTA114YSA TR-SLPLF DTC114YSA TR-SLPLF 2SC1740S TR-SLPLF 2SA933S		
FRONT PCB						
C805 C807 C809 C813 C816			CC73GCH1H220J CK73GB1H102K CK73GB1H102K CE04LW1C470M CK73GB1C104K	CHIP C 22PF J CHIP C 1000PF K CHIP C 1000PF K ELECTRO 47UF 16WV CHIP C 0.10UF K		
C817,8 C819,20 C831 C832 C833-5			CK45FB1C103K CK73GB1H472K CE04KW1C470M CK73GB1H103K CC73GCH1H101J	CERAMIC 0.010UF K CHIP C 4700PF K ELECTRO 47UF 16WV CHIP C 0.010UF K CHIP C 100PF J		
C836,7 C838 C839			CK45FB1H473K CK45FB1E103K CE04LW1H010M	CERAMIC 0.047UF K CERAMIC 0.010UF K ELECTRO 1.0UF 50WV		
N809 N810 NJ81 NJ83			E41-0823-08 E35-3017-08 E63-1272-08 E11-0957-08	CONN 1.25MM 11 55124780 CONN 1.25MM 33 55129060 CON PHONO SCKT 55191980 CONN-PHJAC 3.5 55198170		
L801 L816		*	L31-0668-08 L31-0668-08	LF 47U0H +10% 55168840 LF 47U0H +10% 55168840		
J801 J803,4 J821 J823 J824			RK73GB1J000J RK73GB1J000J RK73GB1J000J RK73GB1J000J RK73GB1J000J	CHIP R 0 J 1/16W CHIP R 0 J 1/16W CHIP R 0 J 1/16W CHIP R 0 J 1/16W CHIP R 0 J 1/16W		
J841 R801 R802 R803,4 R805			RK73GB1J000J RK73GB1J102J RK73GB1J820J RK73GB1J221J RK73GB1J122J	CHIP R 0 J 1/16W CHIP R 1.0K J 1/16W CHIP R 82 J 1/16W CHIP R 220 J 1/16W CHIP R 1.2K J 1/16W		
R806 R807 R808 R809,10 R811			RK73GB1J152J RK73GB1J223J RK73GB1J822J RK73GB1J224J RK73GB1J222J	CHIP R 1.5K J 1/16W CHIP R 22K J 1/16W CHIP R 8.2K J 1/16W CHIP R 220K J 1/16W CHIP R 2.2K J 1/16W		

L : Scandinavia K : USA P : Canada R : Mexico C : China I : Malaysia
Y : PX(Far East,Hawaii) T : England E : Europe G : Germany V : China(Shanghai)
Y : AAFES(Europe) X : Australia Q : Russia H : Korea M : Other Areas △ indicates safety critical components .

PARTS LIST

DVR-605

* New Parts
Parts without **Parts No.** are not supplied.
Les articles non mentionnés dans le **Parts No.** ne sont pas fournis.
Teile ohne **Parts No.** werden nicht geliefert.

7

Ref. No	Add-ress	New Parts	Parts No.	Description	Desti-nation	Re-marks
R816			RK73GB1J102J	CHIP R 1.0K J 1/16W		
R817			RK73GB1J101J	CHIP R 100 J 1/16W		
R820,1			RK73GB1J153J	CHIP R 15K J 1/16W		
R822,3			RK73GB1J010J	CHIP R 1 J 1/16W		
R831			RK73GB1J103J	CHIP R 10K J 1/16W		
R832			RK73GB1J471J	CHIP R 470 J 1/16W		
R833			RK73GB1J102J	CHIP R 1.0K J 1/16W		
R834,5			RK73GB1J103J	CHIP R 10K J 1/16W		
R836			RK73GB1J102J	CHIP R 1.0K J 1/16W		
R837			RK73GB1J101J	CHIP R 100 J 1/16W		
R838			RK73GB1J102J	CHIP R 1.0K J 1/16W		
R841-6			RK73GB1J181J	CHIP R 180 J 1/16W		
R848			RK73GB1J102J	CHIP R 1.0K J 1/16W		
R849			RK73GB1J122J	CHIP R 1.2K J 1/16W		
R850			RK73GB1J152J	CHIP R 1.5K J 1/16W		
R851			RK73GB1J222J	CHIP R 2.2K J 1/16W		
R852			RK73GB1J272J	CHIP R 2.7K J 1/16W		
R853			RK73GB1J104J	CHIP R 100K J 1/16W		
R854			RK73GB1J332J	CHIP R 3.3K J 1/16W		
R855			RK73GB1J562J	CHIP R 5.6K J 1/16W		
R881-99			RK73GB1J104J	CHIP R 100K J 1/16W		
S831-40		*	S70-0087-08	SWITACT VERTIC 55145270		
S841			S90-0152-08	SWIPUSH VERTIC 55155850		
S842			T99-0668-08	PR-ROT 10K0 OH 55191680		
D802-8			UDZ5.1	D-ZENER UDZ 5.1		
D811,2			UDZ5.1	D-ZENER UDZ 5.1		
D830			1SS355	D-SLP 1SS355		
D831,2			1N4148	D-SLP 1N4148		
D833-8			B30-2638-08	D-LEM L-7104SR 55192130		
DP81			HNW-11SM18	DISPLAY HNW-11 55161410		
IC81			BU4094BF	IC(8bit SHIFT/STORE REGISTER)		
Q831-5			DTC114YKA	TR-SSD DTC114YKA		
Q836			DTA114YKA	TR-SSD DTA114YKA		
X831			W02-2935-08	IC-REMOTE 55193920		
NJ82		*	W02-2961-08	IC-OPT 55311530		
DVD PCB (PROGRESSIVE SCAN)						
C 10B			CE04LW1C100M	ELECTRO 10UF 16WV		
C 10G			CE04LW1C100M	ELECTRO 10UF 16WV		
C 10R			CE04LW1C100M	ELECTRO 10UF 16WV		
C 11B			CE04LW1C100M	ELECTRO 10UF 16WV		
C 11G			CE04LW1C100M	ELECTRO 10UF 16WV		
C 11R			CE04LW1C100M	ELECTRO 10UF 16WV		
C 12B			CE04LW1H010M	ELECTRO 1.0UF 50WV		
C 12C			CK73GB1H103K	CHIP C 0.010UF K		
C 12G			CK73GB1C104K	CHIP C 0.10UF K		
C 12R			CE04LW1H010M	ELECTRO 1.0UF 50WV		
C 12Y			CK73GB1C104K	CHIP C 0.10UF K		
C 13B			CE04LW1C101M	ELECTRO 100UF 16WV		
C 13C			CK73GB1C104K	CHIP C 0.10UF K		
C 13G			CE04LW1C101M	ELECTRO 100UF 16WV		
C 13R			CE04LW1C101M	ELECTRO 100UF 16WV		
C 13Y			CE04LW1C101M	ELECTRO 100UF 16WV		
C 14B			CE04LW1C220M	ELECTRO 22UF 16WV		

L : Scandinavia K : USA P : Canada R : Mexico C : China I : Malaysia
Y : PX(Far East,Hawaii) T : England E : Europe G : Germany V : China(Shanghai)
Y : AAFES(Europe) X : Australia Q : Russia H : Korea M : Other Areas ⚠ indicates safety critical components .

* New Parts
Parts without **Parts No.** are not supplied.
Les articles non mentionnés dans le **Parts No.** ne sont pas fournis.
Teile ohne **Parts No.** werden nicht geliefert.

8

Ref. No	Add-ress	New Parts	Parts No.	Description	Desti-nation	Re-marks
C 14G			CE04LW1C220M	ELECTRO 22UF 16WVC	14R	
C14R			CE04LW1C220M	ELECTRO 22UF 16WV		
C 14Y			CE04LW1C220M	ELECTRO 22UF 16WV		
C113			CK73GB1C104K	CHIP C 0.10UF K		
C115			CE04LW1C101M	ELECTRO 100UF 16WV		
C117			CE04LW1C101M	ELECTRO 100UF 16WV		
C122			CE04LW1C101M	ELECTRO 100UF 16WV		
C124			CE04LW1C101M	ELECTRO 100UF 16WV		
C130			CE04LW1C101M	ELECTRO 100UF 16WV		
C132-4			CK73GB1C104K	CHIP C 0.10UF K		
C135			CE04LW1C220M	ELECTRO 22UF 16WV		
C136-40			CK73GB1H102K	CHIP C 1000PF K		
C141			CK73GB1C104K	CHIP C 0.10UF K		
C142-8			CK73GB1H102K	CHIP C 1000PF K		
C149-51			CC73GCH1H470J	CHIP C 47PF J		
C152			CK73GB1H102K	CHIP C 1000PF K		
C153			CK73GB1H103K	CHIP C 0.010UF K		
L 25B			RK73GB1J000J	CHIP R 0 J 1/16W		
L 25C			RK73GB1J000J	CHIP R 0 J 1/16W		
L 25G			RK73GB1J000J	CHIP R 0 J 1/16W		
L 25R			RK73GB1J000J	CHIP R 0 J 1/16W		
L 25S			RK73GB1J000J	CHIP R 0 J 1/16W		
L 25Y			RK73GB1J000J	CHIP R 0 J 1/16W		
R 11B			RK73GB1J100J	CHIP R 10 J 1/16W		
R 11C			RK73GB1J100J	CHIP R 10 J 1/16W		
R 11G			RK73GB1J100J	CHIP R 10 J 1/16W		
R 11R			RK73GB1J100J	CHIP R 10 J 1/16W		
R 11S			RK73GB1J100J	CHIP R 10 J 1/16W		
R 11Y			RK73GB1J100J	CHIP R 10 J 1/16W		
R 12B			RK73GB1J562J	CHIP R 5.6K J 1/16W		
R 12G			RK73GB1J562J	CHIP R 5.6K J 1/16W		
R 12R			RK73GB1J562J	CHIP R 5.6K J 1/16W		
R 13B			RK73GB1J363J	CHIP R 36K J 1/16W		
R 13G			RK73GB1J363J	CHIP R 36K J 1/16W		
R 13R			RK73GB1J363J	CHIP R 36K J 1/16W		
R 14B			RK73GB1J222J	CHIP R 2.2K J 1/16W		
R 14G			RK73GB1J222J	CHIP R 2.2K J 1/16W		
R 14R			RK73GB1J222J	CHIP R 2.2K J 1/16W		
R 15B			RK73GB1J681J	CHIP R 680 J 1/16W		
R 15G			RK73GB1J681J	CHIP R 680 J 1/16W		
R 15R			RK73GB1J681J	CHIP R 680 J 1/16W		
R 16B			RK73GB1J363J	CHIP R 36K J 1/16W		
R 16G			RK73GB1J363J	CHIP R 36K J 1/16W		
R 16R			RK73GB1J363J	CHIP R 36K J 1/16W		
R 17B			RK73GB1J562J	CHIP R 5.6K J 1/16W		
R 17G			RK73GB1J562J	CHIP R 5.6K J 1/16W		
R 17R			RK73GB1J562J	CHIP R 5.6K J 1/16W		
R 18B			RK73GB1J102J	CHIP R 1.0K J 1/16W		
R 18G			RK73GB1J102J	CHIP R 1.0K J 1/16W		
R 18R			RK73GB1J102J	CHIP R 1.0K J 1/16W		
R 19B			RK73GB1J101J	CHIP R 100 J 1/16W		
R 19G			RK73GB1J101J	CHIP R 100 J 1/16W		
R 19R			RK73GB1J101J	CHIP R 100 J 1/16W		
R 20B			RK73GB1J750J	CHIP R 75 J 1/16W		

L : Scandinavia K : USA P : Canada R : Mexico C : China I : Malaysia
Y : PX(Far East,Hawaii) T : England E : Europe G : Germany V : China(Shanghai)
Y : AAFES(Europe) X : Australia Q : Russia H : Korea M : Other Areas ⚠ indicates safety critical components .

PARTS LIST

* New Parts

Parts without **Parts No.** are not supplied.

Les articles non mentionnés dans le **Parts No.** ne sont pas fournis.

Teile ohne **Parts No.** werden nicht geliefert.

9

Ref. No	Add-ress	New Parts	Parts No.	Description	Desti-nation	Re-marks
R 20G			RK73GB1J121J	CHIP R 120 J 1/16W		
R 20R			RK73GB1J750J	CHIP R 75 J 1/16W		
R 23B			RK73GB1J1372F	CHIP R 13.7K F 1/16W		
R 23G			RK73GB1J1372F	CHIP R 13.7K F 1/16W		
R 23R			RK73GB1J1372F	CHIP R 13.7K F 1/16W		
R 24B			RK73GB1J1372F	CHIP R 13.7K F 1/16W		
R 24G			RK73GB1J1372F	CHIP R 13.7K F 1/16W		
R 24R			RK73GB1J1372F	CHIP R 13.7K F 1/16W		
R 25B			RK73GB1J750J	CHIP R 75 J 1/16W		
R 25C			RK73GB1J750J	CHIP R 75 J 1/16W		
R 25G			RK73GB1J750J	CHIP R 75 J 1/16W		
R 25R			RK73GB1J750J	CHIP R 75 J 1/16W		
R 25S			RK73GB1J750J	CHIP R 75 J 1/16W		
R 25Y			RK73GB1J750J	CHIP R 75 J 1/16W		
R147			RK73GB1J100J	CHIP R 10 J 1/16W		
R161			RK73GB1J000J	CHIP R 0 J 1/16W		
R162-4			RK73GB1J101J	CHIP R 100 J 1/16W		
R165-72			RK73GB1J470J	CHIP R 47 J 1/16W		
R173,4			RK73GB1J101J	CHIP R 100 J 1/16W		
R175			RK73GB1J332J	CHIP R 3.3K J 1/16W		
R176			RK73FB2A142F	CHIP R 1.4K F 1/10W		
R177			RK73GB1J362J	CHIP R 3.6K J 1/16W		
R178			RK73GB1J820J	CHIP R 82 J 1/16W		
R179			RK73GB1J361J	CHIP R 360 J 1/16W		
R180			RK73GB1J2R2J	CHIP R 2.2 J 1/16W		
R181			RK73GB1J100J	CHIP R 10 J 1/16W		
R182			RK73GB1J2R2J	CHIP R 2.2 J 1/16W		
R183-6			RK73GB1J473J	CHIP R 47K J 1/16W		
R187,8			RK73GB1J2R2J	CHIP R 2.2 J 1/16W		
R189,90			RK73GB1J100J	CHIP R 10 J 1/16W		
R191,2			RK73GB1J473J	CHIP R 47K J 1/16W		
R193,4			RK73GB1J101J	CHIP R 100 J 1/16W		
R195			RK73GB1J472J	CHIP R 4.7K J 1/16W		
R196			RK73GB1J102J	CHIP R 1.0K J 1/16W		
VR11		*	R39-0048-08	PR 200R0 OHM 55307870		
D101			1SS355	D-SLP 1SS355		
IC 11			PM0026A	IC(LINE DOUBLER IC)		
IC 12		*	MM1568AJBE	IC-VIDEOPROC MM1568AJBE		
IC 13			TL431	IC-REGSPECKT TL431		
IC 14			MC74HC74AD	IC-SPECFUNC MC74HC74AD		
IC 15			74HC86	IC-LOGIC 74HC86		
Q 10B			DTC114YKA	TR-SSD DTC114YKA		
Q 10G			DTC114YKA	TR-SSD DTC114YKA		
Q 10R			DTC114YKA	TR-SSD DTC114YKA		
Q 11B			KTN2222AS	TR-SLPSWA KTN2222AS		
Q 11G			KTN2222AS	TR-SLPSWA KTN2222AS		
Q 11R			KTN2222AS	TR-SLPSWA KTN2222AS		
Q 12B			KTN2222AS	TR-SLPSWA KTN2222AS		
Q 12G			KTN2222AS	TR-SLPSWA KTN2222AS		
Q 12R			KTN2222AS	TR-SLPSWA KTN2222AS		
Q 13B			KTN2907A	TR-SLPSWA KTN2907AS		
Q 13G			KTN2907A	TR-SLPSWA KTN2907AS		
Q 13R			KTN2907A	TR-SLPSWA KTN2907AS		
Q 14B			DTC114YKA	TR-SSD DTC114YKA		
Q 14G			DTC114YKA	TR-SSD DTC114YKA		

L : Scandinavia Y : PX(Far East,Hawaii) Y : AAFES(Europe) K : USA T : England X : Australia P : Canada E : Europe Q : Russia R : Mexico G : Germany H : Korea C : China V : China(Shanghai) M : Other Areas I : Malaysia A indicates safety critical components .

* New Parts

Parts without **Parts No.** are not supplied.

Les articles non mentionnés dans le **Parts No.** ne sont pas fournis.

Teile ohne **Parts No.** werden nicht geliefert.

10

Ref. No	Add-ress	New Parts	Parts No.	Description	Desti-nation	Re-marks
Q 14R			DTC114YKA	TR-SSD DTC114YKA		
Q 15B			KTN2907A	TR-SLPSWA KTN2907AS		
Q 15G			KTN2907A	TR-SLPSWA KTN2907AS		
Q 15R			KTN2907A	TR-SLPSWA KTN2907AS		
Q101			DTA114YKA	TR-SSD DTA114YKA		
Q102			DTC114YKA	TR-SSD DTC114YKA		
Q103			KTC3875Y	TR-SLPSWA KTC3875Y		
MICROPROCESSOR						
C501			CK73GB1C104K	CHIP C 0.10UF K		
C502			CK73GB1H223K	CHIP C 0.022UF K		
C503			CK73GB1C104K	CHIP C 0.10UF K		
C504			CK73GB1H102K	CHIP C 1000PF K		
C505			CE04LW1H010M	ELECTRO 1.0UF 50WV		
C506			CE04LW1A101M	ELECTRO 100UF 10WV		
C507			CE04LW1H2R2M	ELECTRO 2.2UF 50WV		
C508,9			CK73GB1H102K	CHIP C 1000PF K		
C551,2			CC73GCH1H221J	CHIP C 220PF J		
C553,4			CE04LW1C100M	ELECTRO 10UF 16WV		
C555,6			CK73GB1C104K	CHIP C 0.10UF K		
C557,8			CE04LW1A471M	ELECTRO 470UF 10WV		
C559,60			CE04LW1C100M	ELECTRO 10UF 16WV		
C561,2			CC73GCH1H101J	CHIP C 100PF J		
C563,4			CE04LW1A471M	ELECTRO 470UF 10WV		
C565			CK73GB1H223K	CHIP C 0.022UF K		
C588,9			CC73GCH1H101J	CHIP C 100PF J		
C590			CK73GB1C104K	CHIP C 0.10UF K		
C591			CE04LW1A471M	ELECTRO 470UF 10WV		
C592			CE04LW1E330M	ELECTRO 33UF 25WV		
C598,9			CK73GB1H102K	CHIP C 1000PF K		
N506			E41-0799-08	CONN 1.25MM 19 55129010		
N507			E41-0824-08	CONN 1.25MM 13 55124790		
N509			E41-0823-08	CONN 1.25MM 11 55124780		
N510			E35-3017-08	CONN 1.25MM 33 55129060		
N511			E40-8777-08	CONN 2.0MM 5 M 55123320		
NJ51		*	E63-1289-08	CON PHONO SCKT 55115040		
NJ52		*	E63-1290-08	CON PHONO SCKT 55181170		
NJ53		*	E63-1243-08	CON DIN SCKT M 55149520		
L501		*	L31-0668-08	LF 47U0H +10% 55168840		
Y501			L77-2355-08	CRESONATOR 10M 55126140		
J502			RK73GB1J000J	CHIP R 0 J 1/16W		
J593			RK73GB1J000J	CHIP R 0 J 1/16W		
R501,2			RK73GB1J103J	CHIP R 10K J 1/16W		
R504,5			RK73GB1J102J	CHIP R 1.0K J 1/16W		
R512,3			RK73GB1J102J	CHIP R 1.0K J 1/16W		
R514-7			RK73GB1J103J	CHIP R 10K J 1/16W		
R518,9			RK73GB1J472J	CHIP R 4.7K J 1/16W		
R520,1			RK73GB1J473J	CHIP R 47K J 1/16W		
R522			RK73GB1J104J	CHIP R 100K J 1/16W		
R523			RK73GB1J103J	CHIP R 10K J 1/16W		
R526-8			RK73GB1J103J	CHIP R 10K J 1/16W		
R529			RK73GB1J104J	CHIP R 100K J 1/16W		
R530			RK73GB1J103J	CHIP R 10K J 1/16W		
R532			RK73GB1J122J	CHIP R 1.2K J 1/16W		

L : Scandinavia Y : PX(Far East,Hawaii) Y : AAFES(Europe) K : USA T : England X : Australia P : Canada E : Europe Q : Russia R : Mexico G : Germany H : Korea C : China V : China(Shanghai) M : Other Areas I : Malaysia A indicates safety critical components .

PARTS LIST

DVR-605

* New Parts

Parts without **Parts No.** are not supplied.

Les articles non mentionnés dans le **Parts No.** ne sont pas fournis.

Teile ohne **Parts No.** werden nicht geliefert.

11

Ref. No	Add-ress	New Parts	Parts No.	Description	Desti-nation	Re-marks
R533			RK73GB1J100J	CHIP R	10 J 1/16W	
R534,5			RK73GB1J470J	CHIP R	47 J 1/16W	
R536			RK73GB1J104J	CHIP R	100K J 1/16W	
R537,8			RK73GB1J103J	CHIP R	10K J 1/16W	
R539			RK73GB1J331J	CHIP R	330 J 1/16W	
R540			RK73GB1J272J	CHIP R	2.7K J 1/16W	
R543			RK73GB1J103J	CHIP R	10K J 1/16W	
R549			RK73GB1J103J	CHIP R	10K J 1/16W	
R550			RK73GB1J563J	CHIP R	56K J 1/16W	
R551			RK73GB1J820J	CHIP R	82 J 1/16W	
R552			RK73GB1J820J	CHIP R	82 J 1/16W	
R558-60			RK73GB1J103J	CHIP R	10K J 1/16W	
R561,2			RK73GB1J750J	CHIP R	75 J 1/16W	
R563			RK73GB1J104J	CHIP R	100K J 1/16W	
R579,80			RK73GB1J103J	CHIP R	10K J 1/16W	
R585			RK73GB1J103J	CHIP R	10K J 1/16W	
R586,687			RK73GB1J221J	CHIP R	220 J 1/16W	
R588,689			RK73GB1J224J	CHIP R	220K J 1/16W	
D501			1N4148	D-SLP	1N4148	
D502-6			1SS355	D-SLP	1SS355	
D507			1N4148	D-SLP	1N4148	
D551,2			1N4148	D-SLP	1N4148	
IC51		*	CXP82860-366Q	IC-MICROCONT	CXP82860-366Q	
IC52			M24C02WMN6	IC-EEPROM	M24C02WMN6	
IC53			NJM2296	IC-SWITCH	NJM2296	
Q501			KTC3875Y	TR-SLPSWA	KTC3875Y	
DVD PCB						
C611			CE04LW1H010M	ELECTRO	1.0UF 50WV	
C612-5			CE04LW1C101M	ELECTRO	100UF 16WV	
C616,7			CE04LW1C470M	ELECTRO	47UF 16WV	
C618			CE04LW1C101M	ELECTRO	100UF 16WV	
C619			CE04LW1H010M	ELECTRO	1.0UF 50WV	
C620			CE04LW1C101M	ELECTRO	100UF 16WV	
C621			CE04LW0J471M	ELECTRO	470UF 6.3WV	
C622-7			CE04LW1C470M	ELECTRO	47UF 16WV	
C628			CE04LW1C101M	ELECTRO	100UF 16WV	
C629			CE04LW1C470M	ELECTRO	47UF 16WV	
C630			CE04LW0J471M	ELECTRO	470UF 6.3WV	
C631			CE04LW1C100M	ELECTRO	10UF 16WV	
C632,3			CE04LW1C101M	ELECTRO	100UF 16WV	
C634			CE04LW0J471M	ELECTRO	470UF 6.3WV	
C637			CE04LW1H010M	ELECTRO	1.0UF 50WV	
C638			CE04LW1C100M	ELECTRO	10UF 16WV	
C639			CE04LW1C101M	ELECTRO	100UF 16WV	
C640			CK73GB1C104K	CHIP C	0.10UF K	
C641			CK73GB1H471K	CHIP C	470PF K	
C642-4			CK73GB1C104K	CHIP C	0.10UF K	
C645,6			CK73GB1H222K	CHIP C	2200PF K	
C647,8			CK73GB1H331K	CHIP C	330PF K	
C649			CC73GCH1H200J	CHIP C	20PF J	
C650,1			CC73GCH1H240J	CHIP C	24PF J	
C652-4			CK73GB1C104K	CHIP C	0.10UF K	
C655,6			CK73GB1H103K	CHIP C	0.010UF K	
C657,8			CK73GB1C104K	CHIP C	0.10UF K	

L : Scandinavia
Y : PX(Far East,Hawaii)
Y : AAFES(Europe)

K : USA
T : England
X : Australia

P : Canada
E : Europe
Q : Russia

R : Mexico
G : Germany
H : Korea

C : China
V : China(Shanghai)
M : Other Areas

I : Malaysia

⚠ indicates safety critical components.

* New Parts

Parts without **Parts No.** are not supplied.

Les articles non mentionnés dans le **Parts No.** ne sont pas fournis.

Teile ohne **Parts No.** werden nicht geliefert.

12

Ref. No	Add-ress	New Parts	Parts No.	Description	Desti-nation	Re-marks
C659			CK73GB1H103K	CHIP C	0.010UF K	
C660-3			CC73GCH1H100D	CHIP C	10PF D	
C664			CK73GB1C104K	CHIP C	0.10UF K	
C665			CK73GB1H103K	CHIP C	0.010UF K	
C666-8			CK73GB1C104K	CHIP C	0.10UF K	
C669,70			CC73GCH1H680J	CHIP C	68PF J	
C671-80			CK73GB1C104K	CHIP C	0.10UF K	
C681,2			CC73GCH1H101J	CHIP C	100PF J	
C683-6			CK73GB1C104K	CHIP C	0.10UF K	
C687-9			CK73GB1H561K	CHIP C	560PF K	
C690			CC73GCH1H100D	CHIP C	10PF D	
C692-4			CK73GB1C104K	CHIP C	0.10UF K	
C695,6			CK73GB1H104K	CHIP C	0.10UF K	
C697			CK73GB1C104K	CHIP C	0.10UF K	
C698-703			CC73GCH1H100D	CHIP C	10PF D	
C715			CE04LW1C101M	ELECTRO	100UF 16WV	
C716-9			CC73GCH1H100D	CHIP C	10PF D	
N601			E40-8771-08	CONN 2.5MM 02	55164790	
N602,3			E35-3010-08	CONN 1.0MM 15	55125910	
N604,5			E41-0800-08	CONN 1.25MM 19	55124760	
L601			L32-1047-08	FBEAD SURFACE	55126670	
L602			L32-1049-08	LF-SMD 22U0H +	14039360	
L603-5			L32-1046-08	LF-SMD 2U2H +1	14041740	
L606,7			L32-1047-08	FBEAD SURFACE	55126670	
L608			L32-1047-08	FBEAD SURFACE	55126670	
L609			L32-1046-08	LF-SMD 2U2H +1	14041740	
L610			L32-1049-08	LF-SMD 22U0H +	14039360	
L611			L32-1047-08	FBEAD SURFACE	55126670	
L616			L32-1049-08	LF-SMD 22U0H +	14039360	
Y601			L77-2326-08	FILQZ 27M0 HZ	55128980	
R601-11			R90-1333-08	LADDER R	47	
R615-8			RK73GB1J470J	CHIP R	47 J 1/16W	
R619-24			RK73GB1J331J	CHIP R	330 J 1/16W	
R625-32			RK73GB1J470J	CHIP R	47 J 1/16W	
R633			RK73GB1J430J	CHIP R	43 J 1/16W	
R634-9			RK73GB1J473J	CHIP R	47K J 1/16W	
R640-2			RK73GB1J103J	CHIP R	10K J 1/16W	
R643,4			RK73GB1J472J	CHIP R	4.7K J 1/16W	
R645			RK73GB1J103J	CHIP R	10K J 1/16W	
R646			RK73GB1J470J	CHIP R	47 J 1/16W	
R647			RK73GB1J102J	CHIP R	1.0K J 1/16W	
R648			RK73GB1J103J	CHIP R	10K J 1/16W	
R649,50			RK73GB1J470J	CHIP R	47 J 1/16W	
R651			RK73GB1J100J	CHIP R	10 J 1/16W	
R652,3			RK73GB1J470J	CHIP R	47 J 1/16W	
R654,5			RK73GB1J182J	CHIP R	1.8K J 1/16W	
R656,7			RK73GB1J101J	CHIP R	100 J 1/16W	
R658,9			RK73GB1J103J	CHIP R	10K J 1/16W	
R660,1			RK73GB1J470J	CHIP R	47 J 1/16W	
R662			RK73GB1J103J	CHIP R	10K J 1/16W	
R663,4			RK73GB1J470J	CHIP R	47 J 1/16W	
R665,6			RK73GB1J473J	CHIP R	47K J 1/16W	
R667,8			RK73GB1J562J	CHIP R	5.6K J 1/16W	
R669			RK73GB1J470J	CHIP R	47 J 1/16W	

L : Scandinavia
Y : PX(Far East,Hawaii)
Y : AAFES(Europe)

K : USA
T : England
X : Australia

P : Canada
E : Europe
Q : Russia

R : Mexico
G : Germany
H : Korea

C : China
V : China(Shanghai)
M : Other Areas

I : Malaysia

⚠ indicates safety critical components.

* New Parts

Parts without **Parts No.** are not supplied.

Les articles non mentionnés dans le **Parts No.** ne sont pas fournis.

Teile ohne **Parts No.** werden nicht geliefert.

13

Ref. No	Add-ress	New Parts	Parts No.	Description	Desti-nation	Re-marks
R670,1 R672 R673,4 R675-8 R679			RK73GB1J392J RK73GB1J470J RK73GB1J912J RK73GB1J470J RK73GB1J824J	CHIP R 3.9K J 1/16W CHIP R 47 J 1/16W CHIP R 9.1K J 1/16W CHIP R 47 J 1/16W CHIP R 820K J 1/16W		
R680-2 R683,4 R685 R686 R687			RK73GB1J470J RK73GB1J103J RK73GB1J470J RK73GB1J101J RK73GB1J560J	CHIP R 47 J 1/16W CHIP R 10K J 1/16W CHIP R 47 J 1/16W CHIP R 100 J 1/16W CHIP R 56 J 1/16W		
R688 R695-8 R699 R700 R741			RK73GB1J105J R90-1333-08 RK73GB1J562J RK73GB1J103J RK73GB1J683J	CHIP R 1.0M J 1/16W LADDER R 47 CHIP R 5.6K J 1/16W CHIP R 10K J 1/16W CHIP R 68K J 1/16W		
R742 R743,4 R746,7 R748 R749			RK73GB1J473J RK73FB2A2002F RK73GB1J103J RK73GB1J100J RK73GB1J103J	CHIP R 47K J 1/16W CHIP R 20.0K F 1/10W CHIP R 10K J 1/16W CHIP R 10 J 1/16W CHIP R 10K J 1/16W		
R750,1 R752 R753 R754 R755,6			RK73GB1J750J RK73GB1J103J RK73GB1J470J RK73GB1J470J RK73GB1J104J	CHIP R 75 J 1/16W CHIP R 10K J 1/16W CHIP R 47 J 1/16W CHIP R 47 J 1/16W CHIP R 100K J 1/16W		
R757 R758,9 R760-3 R764 R765			RK73GB1J470J RK73GB1J102J RK73GB1J472J RK73GB1J473J RK73GB1J000J	CHIP R 47 J 1/16W CHIP R 1.0K J 1/16W CHIP R 4.7K J 1/16W CHIP R 47K J 1/16W CHIP R 0 J 1/16W		
R766 R767-9 R770 R771,2 R773-5			RK73GB1J471J RK73GB1J470J RK73GB1J473J RK73GB1J471J RK73GB1J103J	CHIP R 470 J 1/16W CHIP R 47 J 1/16W CHIP R 47K J 1/16W CHIP R 470 J 1/16W CHIP R 10K J 1/16W		
R776,7 R778 R779 R780-2 R783			RK73GB1J220J RK73GB1J562J RK73GB1J182J RK73GB1J470J RK73GB1J330J	CHIP R 22 J 1/16W CHIP R 5.6K J 1/16W CHIP R 1.8K J 1/16W CHIP R 47 J 1/16W CHIP R 33 J 1/16W		
R784 R785 R795 R797			RK73GB1J330J RK73GB1J473J RK73GB1J472J RK73GB1J430J	CHIP R 33 J 1/16W CHIP R 47K J 1/16W CHIP R 4.7K J 1/16W CHIP R 43 J 1/16W		
D601 D602 D603,4 D605 D606			1N5232B RB441Q-40 1N4148 UDZ2.2B 1SS355	D-ZENER 1N5232B D-SLP RB441Q-40 D-SLP 1N4148 D-ZENER UDZ 2.2 B D-SLP 1SS355		
IC 61 IC 62 IC 63 IC 64 IC 65			STI5519 M24C02WMN6 HY57V641620HGT WM8728 BA4560F	IC-VIDEOPROC STI5519 IC-EEPROM M24C02WMN6 IC-DRAM 100M0 HY57V641620HGT-H IC-CONV WM8728 IC-OPERAMP BA4560F		

L : Scandinavia Y : PX(Far East,Hawaii) Y : AAFES(Europe) K : USA T : England X : Australia P : Canada E : Europe U : Russia R : Mexico G : Germany H : Korea C : China V : China(Shanghai) M : Other Areas I : Malaysia A indicates safety critical components .

* New Parts

Parts without **Parts No.** are not supplied.

Les articles non mentionnés dans le **Parts No.** ne sont pas fournis.

Teile ohne **Parts No.** werden nicht geliefert.

14

Ref. No	Add-ress	New Parts	Parts No.	Description	Desti-nation	Re-marks
IC 66 IC 66 IC 66 IC 67 IC 69			M29W800AT901N1 SST39VF800A904 TMS29LF80 M74HCU04M1R FAN8082	IC-MEMFLASH M29W800AT90N1 IC-MEMFLASH SST39VF800A-90- IC-MEMFLASH TMS29 IC-LOGIC M74HCU04M1R IC-MOTORCIR FAN8082		
Q601,2 Q603,4 Q605 Q607 Q608			KTC3875Y DTC323TK KRA107S KTC3875Y KTA1504Y	TR-SLPSWA KTC3875Y TR-SSD DTC323TK TR-SSD KRA107S TR-SLPSWA KTC3875Y TR-SLPSWA KTA1504Y		
Q609			DTC114YKA	TR-SSD DTC114YKA		
DSP PCB						
C301 C302 C303-5 C306 C307			CK73GB1H102K CK73GB1H103K CK73GB1H102K CC73GCH1H221J CK73GB1H103K	CHIP C 1000PF K CHIP C 0.010UF K CHIP C 1000PF K CHIP C 220PF J CHIP C 0.010UF K		
C308 C309 C310 C312-18 C319			CK73GB1C224K CK73GB1H103K CK73GB1H122K CK73GB1H102K CK73GB1H473K	CHIP C 0.22UF K CHIP C 0.010UF K CHIP C 1200PF K CHIP C 1000PF K CHIP C 0.047UF K		
C320,21 C322 C323 C324 C325,6			CK73GB1H102K CC73GCH1H101J CK73GB1H222K CK73GB1C104K CC73GCH1H101J	CHIP C 1000PF K CHIP C 100PF J CHIP C 2200PF K CHIP C 0.10UF K CHIP C 100PF J		
C327 C329 C330 C331-7 C338			CK73GB1H222K CK73GB1C104K CC73GCH1H221J CK73GB1H102K CK73GB1H122K	CHIP C 2200PF K CHIP C 0.10UF K CHIP C 220PF J CHIP C 1000PF K CHIP C 1200PF K		
C339 C340,1 C342 C343 C344-6			CK73GB1H153K CK73GB1H122K CK73GB1C104K CK73GB1H122K CK73GB1C104K	CHIP C 0.015UF K CHIP C 1200PF K CHIP C 0.10UF K CHIP C 1200PF K CHIP C 0.10UF K		
C347 C348 C349-51 C352 C353-5			CC73GCH1H221J CK73GB1H332K CC73GCH1H221J CC73GCH1H101J CK73GB1H102K	CHIP C 220PF J CHIP C 3300PF K CHIP C 220PF J CHIP C 100PF J CHIP C 1000PF K		
C356 C357 C358 C359 C360			CK73GB1C104K CK73GB1H473K CK73GB1C104K CK73GB1H473K CC73GCH1H101J	CHIP C 0.10UF K CHIP C 0.047UF K CHIP C 0.10UF K CHIP C 0.047UF K CHIP C 100PF J		
C362-7 C368 C369-78 C379 C380			CK73GB1C104K CK73GB1H333K CK73GB1C104K CC73GCH1H470J CC73GCH1H221J	CHIP C 0.10UF K CHIP C 0.033UF K CHIP C 0.10UF K CHIP C 47PF J CHIP C 220PF J		
C381 C382-6			CC73GCH1H470J CK73GB1C104K	CHIP C 47PF J CHIP C 0.10UF K		

L : Scandinavia Y : PX(Far East,Hawaii) Y : AAFES(Europe) K : USA T : England X : Australia P : Canada E : Europe U : Russia R : Mexico G : Germany H : Korea C : China V : China(Shanghai) M : Other Areas I : Malaysia A indicates safety critical components .

PARTS LIST

DVR-605

* New Parts
Parts without **Parts No.** are not supplied.
Les articles non mentionnés dans le **Parts No.** ne sont pas fournis.
Teile ohne **Parts No.** werden nicht geliefert.

15

Ref. No	Add-ress	New Parts	Parts No.	Description	Desti-nation	Re-marks
C387			CC73GCH1H470J	CHIP C 47PF J		
C388-90			CE04LW1C100M	ELECTRO 10UF 16WV		
C391			CE04LW1H2R2M	ELECTRO 2.2UF 50WV		
C392			CE04LW1C470M	ELECTRO 47UF 16WV		
C393			CE04LW1A101M	ELECTRO 100UF 10WV		
C394,5			CE04LW1C100M	ELECTRO 10UF 16WV		
C396			CE04LW1H2R2M	ELECTRO 2.2UF 50WV		
C397			CE04LW1C470M	ELECTRO 47UF 16WV		
C398			CE04LW1C100M	ELECTRO 10UF 16WV		
C399			CE04LW1H010M	ELECTRO 1.0UF 50WV		
C400,1			CE04LW1C100M	ELECTRO 10UF 16WV		
C402			CE04LW1H010M	ELECTRO 1.0UF 50WV		
C403,4			CE04LW1C100M	ELECTRO 10UF 16WV		
C405			CE04LW1H4R7M	ELECTRO 4.7UF 50WV		
C406			CE04LW1A101M	ELECTRO 100UF 10WV		
C407-13			CE04LW1C100M	ELECTRO 10UF 16WV		
C414,5			CE04LW1C221M	ELECTRO 220UF 16WV		
C417			CE04LW1C470M	ELECTRO 47UF 16WV		
C418-20			CE04KW0J102M	ELECTRO 1000UF 6.3WV		
C427,8			CC73GCH1H220J	CHIP C 22PF J		
NJ34			E63-1244-08	CON PHONO SCKT 55164750		
L301-3			L92-0556-08	FBEAD SURFACE 55126690		
L314			L92-0557-08	LF-SMD 33U0H + 55185090		
L317			L92-0557-08	LF-SMD 33U0H + 55185090		
L318-25			L92-0556-08	FBEAD SURFACE 55126690		
L326-8			L32-1047-08	FBEAD SURFACE 55126670		
Y301		*	W02-2962-08	VCXO 12M288 HZ 55348350		
L304			RK73FB2A000J	CHIP R 0 J 1/10W		
L306			RK73FB2A000J	CHIP R 0 J 1/10W		
L308-11			RK73FB2A000J	CHIP R 0 J 1/10W		
L312			RK73GB1J131J	CHIP R 130 J 1/16W		
L313			RK73FB2A000J	CHIP R 0 J 1/10W		
R301			RK73GB1J104J	CHIP R 100K J 1/16W		
R302			RK73GB1J750J	CHIP R 75 J 1/16W		
R303			RK73GB1J682J	CHIP R 6.8K J 1/16W		
R304			RK73GB1J471J	CHIP R 470 J 1/16W		
R305			RK73GB1J561J	CHIP R 560 J 1/16W		
R306			RK73GB1J103J	CHIP R 10K J 1/16W		
R307			RK73GB1J472J	CHIP R 4.7K J 1/16W		
R308			RK73GB1J471J	CHIP R 470 J 1/16W		
R309			RK73GB1J272J	CHIP R 2.7K J 1/16W		
R310			RK73GB1J821J	CHIP R 820 J 1/16W		
R311			RK73GB1J123J	CHIP R 12K J 1/16W		
R312			RK73GB1J472J	CHIP R 4.7K J 1/16W		
R313			RK73GB1J103J	CHIP R 10K J 1/16W		
R314			RK73GB1J333J	CHIP R 33K J 1/16W		
R315,6			RK73GB1J472J	CHIP R 4.7K J 1/16W		
R317			RK73GB1J104J	CHIP R 100K J 1/16W		
R318			RK73GB1J682J	CHIP R 6.8K J 1/16W		
R319,20			RK73GB1J471J	CHIP R 470 J 1/16W		
R321			RK73GB1J272J	CHIP R 2.7K J 1/16W		
R322			RK73GB1J821J	CHIP R 820 J 1/16W		
R323			RK73GB1J104J	CHIP R 100K J 1/16W		

L : Scandinavia K : USA P : Canada R : Mexico C : China I : Malaysia
Y : PX(Far East,Hawaii) T : England E : Europe G : Germany V : China(Shanghai)
Y : AAFES(Europe) X : Australia Q : Russia H : Korea M : Other Areas ⚠ indicates safety critical components .

* New Parts
Parts without **Parts No.** are not supplied.
Les articles non mentionnés dans le **Parts No.** ne sont pas fournis.
Teile ohne **Parts No.** werden nicht geliefert.

16


Ref. No	Add-ress	New Parts	Parts No.	Description	Desti-nation	Re-marks
R324			RK73GB1J562J	CHIP R 5.6K J 1/16W		
R325			RK73GB1J471J	CHIP R 470 J 1/16W		
R326			RK73GB1J472J	CHIP R 4.7K J 1/16W		
R327			RK73GB1J471J	CHIP R 470 J 1/16W		
R328			RK73GB1J272J	CHIP R 2.7K J 1/16W		
R329			RK73GB1J821J	CHIP R 820 J 1/16W		
R330			RK73GB1J104J	CHIP R 100K J 1/16W		
R331			RK73GB1J471J	CHIP R 470 J 1/16W		
R332			RK73GB1J272J	CHIP R 2.7K J 1/16W		
R333			RK73GB1J473J	CHIP R 47K J 1/16W		
R334,5			RK73GB1J103J	CHIP R 10K J 1/16W		
R337,8			RK73GB1J151J	CHIP R 150 J 1/16W		
R339			RK73GB1J203J	CHIP R 20K J 1/16W		
R340			RK73GB1J473J	CHIP R 47K J 1/16W		
R341-3			RK73GB1J103J	CHIP R 10K J 1/16W		
R344,5			RK73GB1J151J	CHIP R 150 J 1/16W		
R346,7			RK73GB1J103J	CHIP R 10K J 1/16W		
R348			RK73GB1J100J	CHIP R 10 J 1/16W		
R349			RK73GB1J222J	CHIP R 2.2K J 1/16W		
R350			RK73GB1J131J	CHIP R 130 J 1/16W		
R351			RK73GB1J104J	CHIP R 100K J 1/16W		
R352			RK73GB1J682J	CHIP R 6.8K J 1/16W		
R353,4			RK73GB1J471J	CHIP R 470 J 1/16W		
R355			RK73GB1J123J	CHIP R 12K J 1/16W		
R356			RK73GB1J473J	CHIP R 47K J 1/16W		
R357			RK73GB1J272J	CHIP R 2.7K J 1/16W		
R358			RK73GB1J821J	CHIP R 820 J 1/16W		
R359			RK73GB1J104J	CHIP R 100K J 1/16W		
R360			RK73GB1J682J	CHIP R 6.8K J 1/16W		
R361			RK73GB1J101J	CHIP R 100 J 1/16W		
R362,3			RK73GB1J471J	CHIP R 470 J 1/16W		
R364,5			RK73GB1J472J	CHIP R 4.7K J 1/16W		
R366			RK73GB1J272J	CHIP R 2.7K J 1/16W		
R367-9			RK73GB1J103J	CHIP R 10K J 1/16W		
R370			RK73GB1J821J	CHIP R 820 J 1/16W		
R371-5			RK73GB1J472J	CHIP R 4.7K J 1/16W		
R376-9			RK73GB1J123J	CHIP R 12K J 1/16W		
R381			RK73GB1J123J	CHIP R 12K J 1/16W		
R382			RK73GB1J203J	CHIP R 20K J 1/16W		
R383			RK73GB1J103J	CHIP R 10K J 1/16W		
R384			RK73GB1J682J	CHIP R 6.8K J 1/16W		
R385			RK73GB1J471J	CHIP R 470 J 1/16W		
R386			RK73GB1J821J	CHIP R 820 J 1/16W		
R387			RK73GB1J102J	CHIP R 1.0K J 1/16W		
R394			RK73GB1J151J	CHIP R 150 J 1/16W		
R395-401			RK73GB1J220J	CHIP R 22 J 1/16W		
R402,3			RK73GB1J3R3J	CHIP R 3.3 J 1/16W		
R404			RK73GB1J911J	CHIP R 910 J 1/16W		
R405,6			RK73GB1J101J	CHIP R 100 J 1/16W		
R407			RK73GB1J242J	CHIP R 2.4K J 1/16W		
R408-16			RK73GB1J100J	CHIP R 10 J 1/16W		
R417-19			RK73GB1J221J	CHIP R 220 J 1/16W		
R425,6			RK73GB1J620J	CHIP R 62 J 1/16W		
IC31			CS4228QFP44	IC COMM CS4228 QFP44		

L : Scandinavia K : USA P : Canada R : Mexico C : China I : Malaysia
Y : PX(Far East,Hawaii) T : England E : Europe G : Germany V : China(Shanghai)
Y : AAFES(Europe) X : Australia Q : Russia H : Korea M : Other Areas ⚠ indicates safety critical components .

* New Parts
 Parts without **Parts No.** are not supplied.
 Les articles non mentionnés dans le **Parts No.** ne sont pas fournis.
 Teile ohne **Parts No.** werden nicht geliefert.

17

Ref. No	Add- ress	New Parts	Parts No.	Description	Desti- nation	Re- marks
IC32 IC33 IC34-8 IC39 IC40,1			AT27LV010A90JC CS493263-CL KIA4558F CS8415A-CS 74VHC244MX	IC-EPROM AT27LV010A-90JC IC-LOWFREQ CS493263-CL IC-OPERAMP KIA4558F IC-LOWFREQ CS8415A-CS IC-LOGIC 74VHC244MX		
IC42,3 Q301			74VHC574MX KTA1504Y	IC-LOGIC F/F 74VHC574MX TR-SLPSWA KTA1504Y		
NJ35			W02-2911-08	D-LEM TOTX178B 55125440		

L : Scandinavia **K** : USA **P** : Canada **R** : Mexico **C** : China **I** : Malaysia
Y : PX(Far East,Hawaii) **T** : England **E** : Europe **G** : Germany **V** : China(Shanghai)
Y : AAFES(Europe) **X** : Australia **Q** : Russia **H** : Korea **M** : Other Areas  indicates safety critical components .

PARTS LIST

DVR-605

DVR-605

SPECIFICATIONS

Main unit

[Amplifier section]

Effective output power during STEREO operation	
1 kHz, 10 % T.H.D. at 6 Ω	40 W + 40 W
Effective output power during SURROUND operation	
Front (1 kHz, 10 % T.H.D. at 6 Ω)	40 W + 40 W
Center (1 kHz, 10 % T.H.D. at 6 Ω)	40 W
Subwoofer (100 Hz, 10 % T.H.D. at 6 Ω)	80 W
Surround (1 kHz, 10 % T.H.D. at 6 Ω)	40 W + 40 W
Input sensitivity / impedance	
VCR / SAT / CABLE / FRONT	600 mV / 68 k Ω
Output level / impedance	
VCR	600 mV / 470 Ω

[Tuner section]

FM tuner section	
Tuning frequency range	87.5 MHz ~ 108 MHz
AM Tuner section	
Tuning frequency range (for U.K., Europe and Australia)	
.....	531 kHz ~ 1,602 kHz
Tuning frequency range (for U.S.A. and Canada)	
.....	530 kHz ~ 1,700 kHz
Tuning frequency range (for other countries)	
.....	531 kHz ~ 1,602 kHz / 530 kHz ~ 1,610 kHz

[DVD/CD/VIDEO CD player section]

Laser	Semiconductor laser
Wow & Flutter	Less than unmeasurable Limit
Video output format (for U.S.A. and Canada)	NTSC
Video output format (for other countries)	NTSC/PAL
VIDEO OUTPUT	
Composite video output level/impedance	1 Vp-p (75 Ω)
S-video output	
Y output level/impedance	1 Vp-p (75 Ω)
C output level/impedance	
NTSC	0.286 Vp-p (75 Ω)
PAL	0.3 Vp-p (75 Ω)
Component video output (only for some areas)	
Y output level/impedance	1 Vp-p (75 Ω)
C/b output level/impedance	0.7 Vp-p (75 Ω)
C/r output level/impedance	0.7 Vp-p (75 Ω)
Compression format	MPEG1/MPEG2

[DIGITAL AUDIO section]

Sampling frequency	32 kHz, 44.1 kHz, 48 kHz
Input level/impedance/wave length	
Optical	-15 dBm ~ 21 dBm (660 nm \pm 30 nm)
Coaxial	0.6 Vp-p (75 Ω)
Digital output	-15 dBm ~ 21 dBm
	(Wave length 660 nm)

[General]

Power consumption	130 W (for U.S.A. and Canada)
	130 W (for U.K.)
	130 W (for other countries)
Dimensions	W: 440 mm (17-5/16")
	H: 93 mm (3-11/16")
	D: 410 mm (16-1/8")
Weight (net)	8.5 kg

KS-306DV Speakers (Front/Surround)

Enclosure	Bass-Reflex type
	(Front Speaker Magnetically shielded)
Speaker configuration	
Woofer	80 mm (3"), cone type
Tweeter	25 mm (1"), balanced dome type

Impedance	6 Ω
Maximum input power	40 W
Dimensions	W: 111 mm (4-3/8")
	H: 156 mm (6-1/8")
	D: 129 mm (5-1/16")

Weight (net)	
Front speakers	0.9 kg (2.0 lb) (1 piece)
Surround speaker	0.8 kg (1.8 lb) (1 piece)

KS-306DV Speakers (Center)

Enclosure	Acoustic Air Suspension type (Magnetically shielded)
Speaker configuration	
Woofer	80 mm (3"), cone type
Tweeter	25 mm (1"), balanced dome type
Impedance	6 Ω
Maximum input power	40 W
Dimensions	W: 252 mm (9-15/16")
	H: 111 mm (4-3/8")
	D: 129 mm (5-1/16")
Weight (net)	1.1 kg (2.4 lb)

SW-06DV Speaker (Subwoofer)

Enclosure	Bass-reflex type (Magnetically shielded)
Speaker configuration	
Woofer	160 mm (6-1/2"), cone type
Impedance	6 Ω
Maximum input power	80 W
Dimensions	W: 120 mm (8-11/16")
	H: 350 mm (13-3/4")
	D: 355 mm (14")
Weight (net)	5.9 kg



1. KENWOOD follows a policy of continuous advancements in development. For this reason specifications may be changed without notice.
2. Sufficient performance may not be possible at very low temperatures (0°C or less).

Note:

Component and circuit are subject to modification to insure best operation under differing local conditions. This manual is based on Europe (E) standard, and provides information on regional circuit modification through use of alternate schematic diagrams, and information on regional component variations through use of parts list.

KENWOOD CORPORATION

2967-3, Ishikawa-machi, Hachioji-shi, Tokyo, 192-8525 Japan

KENWOOD SERVICE CORPORATION

P.O. BOX 22745, 2201 East Dominguez St., Long Beach, CA 90801-5745, U.S.A.